

# **SUPPLY CHAIN MANAGEMENT**

## **THIRUVANANTHAPURAM**

### **SPECIFICATION**

**3 Phase, 4 Wire, CT/PT operated HT Static, bi-directional energy meter of class 0.5S for Border metering**

<b>APPLICABLE TO KSEBL</b>	<b>Rev#0</b>	DOC. NO.: SCM-SPEC/XD/Border Meter
		EFF. DATE: 10.12.2021

Number of Pages: 29

#### **Technical Committee**

1. Chief Engineer- SCM
2. Deputy Chief Engineer -SCM
3. Executive Engineer TMR Thirumala
4. Executive Engineer TMR Pallom
5. Executive Engineer TMR Angamaly
6. Executive Engineer TMR Shoranur
7. Executive Engineer TMR Kannur
8. Executive Engineer(D)-O/o CE-SCM
9. Executive Engineer RITU Kochi



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram  
Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

### TECHNICAL SPECIFICATION

Border meter

Doc. #: SCM-SPEC/XD/EM

Rev.#: 0

Effective Date 10.12.2021

#### (i) Document Approval & Control Status

	Compiled by	Verified by	Approved by
Name	<b>Smt. Suja Maria Paul</b>	<b>Smt. Binu.N</b>	<b>Smt. Prasannakumari.S</b>
Position	Asst. Executive Engineer (O/o Chief Engineer, Supply Chain Management)	Executive Engineer(D) (O/o Chief Engineer, Supply Chain Management)	Chief Engineer (Supply Chain Management)
Date	10.12.21	14.12.21	16.12.21
Signature	Sd/-	Sd/-	Sd/-

#### (ii) Amendments and History

<i>Sec. #</i>	<i>Rev. #</i>	<i>Date</i>	<i>History of Change</i>



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

### TECHNICAL SPECIFICATION

Border meter

Doc. #: SCM-SPEC/XD/EM

Rev.#: 0

Effective Date 10.12.2021

## 1. Purpose

Purpose of this document is to document updates & history, upkeep and publish the specifications related to **THREE PHASE, FOUR WIRE, CT /PT OPERATED, HT, STATIC ENERGY METER OF CLASS 0.5 S or better ACCURACY FOR BORDER METERING** in a professional manner.

## 2. Scope

The Scope of this document is to inform and alert all relevant stakeholders including KSEBL, Public, KSERC etc regarding the current specifications and historical changes adopted in specifications of **THREE PHASE, FOUR WIRE, CT /PT OPERATED, HT, STATIC ENERGY METER OF CLASS 0.5 S or better ACCURACY FOR BORDER METERING** used in field by KSEBL.

## 3. Responsibility

**Executive Engineer (D), Office of Chief Engineer, Supply Chain Management** shall compile and take necessary steps to publish the specification in KSEBL website and shall inform relevant stakeholders regarding updates and revisions.

## 4. Procedure For Revision

Modifications if any, in the technical Specification will be incorporated as **Revisions** . Any changes in values, minor corrections in pages, incorporation of small details etc. will be considered as Minor Modification. **The Revisions due to minor modifications will be assigned as Rev No. 0.1, 0.2 etc .**

A complete updation of the technical specification will be considered as Major modification. **The Revisions due to major modifications will be assigned as Rev No. 1.0, 2.0 etc .**

All the details regarding the revisions (both minor and major ) will be incorporated in “**(ii)-Amendments and history** “ above.

The concerned officers, in consultation with the Technical Committee will review and suggest changes required and the revision suggestion will be approved by **Chief Engineer- SCM**. Those who notice any discrepancy or have any suggestion regarding revision , may bring the matter to the attention of Chief Engineer -SCM in writing or through e-mail id: [cescm@kseb.in](mailto:cescm@kseb.in)



# SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram  
Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

## TECHNICAL SPECIFICATION

Border meter

Doc. #: SCM-SPEC/XD/EM

Rev.#: 0

Effective Date 10.12.2021

### CONTENTS

1. SCOPE .....	5
2. STANDARDS APPLICABLE.....	5
3. SERVICE CONDITIONS.....	5
4. CURRENT & VOLTAGE RATINGS.....	6
5. GENERAL REQUIREMENTS .....	6
6.DESIGN & CONSTRUCTIONAL REQUIREMENTS .....	7
7.OPERATIONAL REQUIREMENTS .....	15
8. CONNECTION DIAGRAM& TERMINAL MARKING .....	17
9. NAME PLATE DETAILS .....	17
10.DATA COMMUNICATION FACILITIES .....	18
11.LOAD SURVEY.....	19
12.TESTS.....	20
13. ROUTINE & ACCEPTANCE TESTS.....	21
14.GUARANTEEE.....	23
15. QUALITY CONTROL.....	24
16.COMPONENT SPECIFICATION.....	24
17.GUARANTEED TECHNICAL PARTICULARS .....	26



# SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram  
Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

## TECHNICAL SPECIFICATION

Border meter

Doc. #: SCM-SPEC/XD/EM

Rev.#: 0

Effective Date 10.12.2021

### **TECHNICAL SPECIFICATION FOR THREE PHASE, FOUR WIRE, CT /PT OPERATED, HT, STATIC ENERGY METER OF CLASS 0.5 S or better ACCURACY FOR BORDER METERING**

#### 1.0. Scope:-

This specification covers the design, manufacture, testing and supply of 3 phase, 4 wire, HT CT/PT operated, bi-directional energy meter of CAT-B type , accuracy class 0.5S or better for both Active and Reactive energy, -/5A, HT static tri vector meter with TOD register, DLMS compliant & AMR compatible with optical port and RS 232 port having ISI Marking, suitable for measurement of active kWh, reactive energy kVARh and apparent energy kVAh and kVA MD, kW MD at nominal frequency in the range of 47.5 Hz to 52.5 Hz in balanced as well as unbalanced load conditions. The type of meter shall be surface/base mounted.

#### 2.0. STANDARDS APPLICABLE

- a. CBIP Guide on Static Energy Meter- Specifications & Testing Pub No.325, January 2015
- b. AC Static Transformer operated Whr. and VARhr. Meters: IS 14697/ 99 Cl.0.2S &0.5S Re affirmed 2004/ IEC 62016-21.
- c. Degree of Protection : IS 12063
- d. Testing equipment for AC Electrical Energy meter : IS 12346
- e. Assembling Standard of Electronic components : ANSI/IPC-A-610
- f. EMC- Testing and measurement techniques, : IEC 61000-4-5/ 2001- 04 Surge immunity test
- g. Basic environmental Testing procedures for : IS 9000 and electronic and electric items latest amendments thereof
- h. Guidelines on Data exchange for electricity
- i. Meter reading, Tariff & Load control : IS 15959 Companion specification
- j. Harmonic measurement & its limits : IEEE519-1992
- k. CEA (Technical standards for connectivity to grid) regulations 2007 for harmonic limits
- l. In case of any conflict or discrepancy, the order of precedence shall be

1. IS

2. Manual of standardization of AC static electrical energy meters, CBIP 325

3. IEC.

In case of any difference between provisions of these standards and the provisions of this specification, the provisions contained in this specification shall prevail.

#### 3. SERVICE CONDITIONS

The meters to be supplied against this specification shall be suitable for satisfactory continuous operation under the following tropical conditions:

- a. Maximum Annual Rainfall (mm) - 5000
- b. Average Annual Rainfall (mm) - 3107
- c. Average no. of thunderstorm days/annum (Isoceraunic level) - 50
- d. Average number of dust storm days per annum - 5
- e. Average number of rainy days per annum - 120-1-40
- f. Specified operation range of temperature - 0°C to 55°C
- g. Limit of range of operation of temperature - 10° C to 60 ° C
- h. Limit of temperature range for storage and transport -10°C to 70°C
- i. Relative humidity (%) - 50-99



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram  
Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

### TECHNICAL SPECIFICATION

#### Border meter

Doc. #: **SCM-SPEC/XD/EM**

Rev.#: 0

Effective Date 10.12.2021

- j. No. of months during which tropical monsoon conditions prevail - 5
- k. Moderately hot and humid climate, conducive to rust and fungus growth.
- l. Seismic level (Horizontal accn) - 0.3 g
- m. Iso-ceraunic level (days per year) - 50
- n. Maximum Wind Pressure - 150 kg sqmt.

#### 4. CURRENT & VOLTAGE RATINGS

- a. Voltage rating: 110V between phase and 110/ $\sqrt{3}$  V between phase and neutral.
- b. Voltage variation: +20% to -40%
- c. Standard Basic Current  $I_b$  : 5 A
- d. Rated maximum current  $I_{max}$ : 200% of  $I_b$
- e. Standard frequency: 50Hz  $\pm$  5%
- f. Power Factor: should work for zero to UPF (lag and lead).
- g. Class of accuracy: **0.5S** for both kWh or kVARh
- h. System of measurement: The meter is intended for 3 phase 4 wire of rating 3x110/ $\sqrt{3}$  5A, 50Hz

#### 5. GENERAL REQUIREMENTS

5.1 Meter shall bear ISI mark.

5.1.1 Meter shall have S mark certification.

5.2 The standard reference temperature for performance shall be 27°C $\pm$ 2°C. If tests are made at a temperature other than that of reference temperature, the results shall be corrected by applying the appropriate temperature coefficient of the meter.

5.3 Unless otherwise specified, the meter should conform to all applicable clauses of standards specified above.

5.4 The meter should start registering the energy at 0.1 % of basic current.

5.5 The meter shall withstand and operate satisfactorily without loss of accuracy under the most hazardous tropical climatic conditions including that specified above.

##### 5.6 Class of Accuracy

5.6.1 The class of accuracy of meter should be **0.5S or better** for both kWh meter and kVARh meter.

5.6.2 The meter should show the readings having an error less than the limits of permissible percentage for all values of current between 5% of basic current and of the maximum current for all power factor as stipulated in standards when it is under balanced loads and under reference conditions.

5.6.3 The accuracy shall not drift with time.

5.6.4 The meter shall be able to carry for 0.5 second a current equal to 20 times the maximum current and the variation in percentage error should not exceed 0.1%.

5.6.5 Voltage dips and interruptions shall not produce a change in register of more than 0.002 kWh/0.003kVAh.

5.6.6 In case any drift is noticed in the accuracy of the meter, which is beyond the permissible limits, the concerned meter shall be withdrawn from service and the manufacturer shall supply a new meter without any extra cost as a replacement (with in three months of receipt from KSEBL), during the guarantee period. Delay in replacement, will be treated as per the clause specified for replacement of faulty meter.

5.6.7 The accuracy of the meter should not be affected with the application of abnormal voltage/frequency generating device.



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram  
Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

### TECHNICAL SPECIFICATION

#### Border meter

Doc. #: **SCM-SPEC/XD/EM**

Rev.#: 0

Effective Date 10.12.2021

1. On any of the phases or neutral terminals

2. On any connecting wires of the meter

or

3. At any place in the load circuit, the accuracy of the meter shall be checked before and after the application of above device.

#### **5.7 Power Consumption**

5.7.1 Voltage Circuit: The active & apparent power consumption of voltage circuit including power supply of meter at reference voltage, reference temperature & frequency shall not exceed 1.0 Watt & 4.0 VA per phase.

5.7.2 Current Circuit: The apparent power taken by current circuit at basic current, reference frequency & reference temperature shall not exceed 1.0 VA/phase.

5.7.3 The apparent and active power consumption of each circuit of a meter at reference voltage/ current mentioned above is for reference frequency and reference temperature.

#### **6 DESIGN AND CONSTRUCTIONAL REQUIREMENTS**

6.1 Meters shall be designed and constructed in such a way that in normal conditions, working personal safety against electric shock and non effectiveness of excessive temperature are ensured.

6.2 Meters shall be projection type and shall have IP 51 degree of protection.

6.3 Direct Sunrays may be falling on the Energy Meter and it shall be designed to withstand the temperature.

6.4 Unless otherwise specified, features of meter should be that of insulating encased meter of protective class II as elaborated under CBIP Guide No.325.

#### **6.5 Design**

6.5.1 All insulating materials used in the construction of the meter shall be substantially non-hygroscopic, non ageing and of tested quality.

6.5.2 Parts and surfaces, which are subjected to corrosion, shall be provided with protective coating to achieve durable results.

6.5.3 The meter shall have a wireless design.

6.5.4 The meter shall have a Test Output (kWh & kVArh), Operation Indicator. The operation indicator must be visible from the front and test output device shall be provided in the form of LED.

6.5.5 Meter shall be designed with application specific integrated circuit (ASIC) or micro controller; shall have no moving part; electronic components shall be assembled on printed circuit board using surface mounting technology (SMT).

6.5.6 Factory calibration using high accuracy software based test bench shall be used considering the error of standard in over all accuracy as per table 1 of IS 12346.

6.5.7 Assembly of electronic components shall be as per ANSI/IPC-A-610 standard.

6.5.8 Internal power supply circuit shall be designed using highly reliable components. Critical components such as metering ICs (ASIC), Microcontroller etc. shall be procured from STACK or IECQ registered suppliers.

6.5.9 The measurement by meter shall not get influenced by injection of high frequency AC



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram  
Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

### TECHNICAL SPECIFICATION

#### Border meter

Doc. #: **SCM-SPEC/XD/EM**

Rev.#: 0

Effective Date 10.12.2021

Voltage/chopped signal / DC signal and harmonics on the terminals of the meter.

- 6.5.10 The meter's accuracy shall not be affected at all by magnetic field from all sides of the meter i.e front, sides, top and bottom of the meter.
- 6.5.11 Power supply unit in the meter should be transformer less, preferably micro controller type to avoid magnetic influence.
- 6.5.12 The meter shall record and display total energy including harmonic energy.
- 6.5.13 The meter shall not generate conducted or radiated noises, which could interfere with other equipment in the system.
- 6.5.14 While installing the meter, it should be possible to check the correctness of current and voltage connections to the meter with proper polarity. This may be available in the display of the meter for different ways the voltage and current are injected.
- 6.5.15 Under normal conditions of use, electrical circuits and insulation shall not reach a temperature which might adversely affect the operation of the meter.
- 6.5.16 The temperature rise at any point of the external surface of the meter should not exceed 20 °C at an ambient temperature at 25 °C to 45 °C.
- 6.5.17 Meter shall withstand an impulse voltage of 6 kV<sub>peak</sub> as per IS14697. The waveform and the generator characteristics used for testing shall be in accordance with IEC 62052-11, clause 7.3.2
- 6.5.18 kVAh measurement should be the vector sum of active and reactive energy, even though the vector sum value tends to be the same as arithmetic sum value while calculating the kVAh as above.

#### 6.6 TOD Timings

The meter should have set for three time zones as given below

- a. 6:00 hours to 18:00 hours
- b. 18:00 hours to 22:00 hours
- c. 22:00 hours to 6:00 hours

#### 6.7 Manufacturing Process, Assembly, Testing

- 6.7.1 Meters shall be manufactured using latest and 'state of the art' technology and methods prevalent in electronics industry. All inward flow of major components and sub assembly parts(CT,PT,RTCs/Crystal,LCDs,LEDs,power circuit electronic components etc.) shall have batch and source identification.
- 6.7.2 Multi-layer 'PCB' assembly with 'PTH' (Plated through Hole) using surface mounted component shall have adequate track clearance for power circuits.
- 6.7.3 SMT component shall be assembled using automatic 'pick-and-place' machines with in process 7 stages, Re-flow Soldering oven, for stabilized setting of the components on 'PCB'. For soldered PCBs, cleaning and washing of cards, after wave soldering process is to be carried out as a standard practice.
- 6.7.4 Assembly line of the manufacturing system shall have provision for testing of sub- assembled cards. Manual placing of components and soldering, is to be minimized to items, which cannot be handled by automatic machine.
- 6.7.5 Handling of 'PCB' with ICs/C-MOS components is to be restricted to bare minimum and precautions to prevent 'ESD' failure to be provided.





## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

### TECHNICAL SPECIFICATION

Border meter

Doc. #: SCM-SPEC/XD/EM

Rev.#: 0

Effective Date 10.12.2021

- 6.7.6 Complete assembled and soldered PCB should under go functional testing using computerized Automatic Test Equipment.
- 6.7.7 Test points should be provided to check the performance of each block/stage of the meter circuitry.
- 6.7.8 Testing at intermediate and final stage is to be carried out with testing instruments, duly calibrated with reference standard, with traceability of source and date.

#### 6.8 Construction.

##### 6.8.1 Meter Base& Cover

- 6.8.1.1 The meter base & cover shall be ultrasonically welded and should be continuous and made out of unbreakable, high grade , fire resistant. Polycarbonate material so as to give it tough and non-breakable qualities which is unbreakable, corrosion resistant & inert to chemicals, flame retardant, immune to ultra violet radiation.
- 6.8.1.2 The meter case and cover should meet UV aging test as per ASTM standards.
- 6.8.1.3 The manufacturer shall indicate hardness , melting temperature and tensile yield strength of the material and necessary test certificate of the same shall be furnished.
- 6.8.1.4 The top cover and terminal cover shall be transparent.
- 6.8.1.5 The thickness of material for meter body should be 2mm minimum.
- 6.8.1.6 Polycarbonate or acrylic or holographic seals shall be used. Lead seals are not permitted at all. The polycarbonate material used shall conform to the test requirement of heat deflection test as per ISO:75 and glow wire test as per the relevant standard.
- 6.8.1.7 The meter shall be provided with adequate shielding to withstand external magnetic influence from all directions as per CBIP guide No.325/2015.
- 6.8.1.8 The housing shall be provided with a keyhole on the top for fixing, which will not be accessible to the outsider after mounting and the terminal cover sealed.
- 6.8.1.9 Along with each meter, inside the packing, leaflet/manual of meter which shall match with the specification of the meter supplied. It shall include the list of full display parameters of the meter supplied.

##### 6.8.2 Terminal Arrangement, Terminal Block and Cover

- 6.8.2.1 Terminals may be grouped in (a) terminal block(s) having adequate insulating properties and mechanical strength.
- 6.8.2.2 The terminal arrangement and connection diagram shall conform to IS: 14697. Terminal arrangement shall be marked on terminals as well as in the connection diagram. The diagram shall show the phase sequence for which the meter is intended.
- 6.8.2.3 Terminals shall be designed to carry  $I_{max}$  continuously and under this condition the temperature at the terminal block shall not exceed  $70^{\circ}\text{C}$  with ambient temperature within operating temperature range as defined by IS 14697.
- 6.8.2.4 Clamping screws should be provided inside the terminal cover and should have metallic sleeve moulded within the block to avoid damage during tightening of the screws.
- 6.8.2.5 The terminal block shall have adequate insulating properties and mechanical strength. The terminal block shall be made from best quality non- hygroscopic, flame retardant polycarbonate material or any other superior industrial plastic material (capable of passing the flammability tests give in IS: 11731) with nickel-plated brass inserts for connecting terminals. The material shall be capable of passing the test given in ISO: 75 for temperature of  $135^{\circ}\text{C}$  and pressure of 1.8 MPa.
- 6.8.2.6 The termination arrangement shall be provided with an extended transparent terminal cover as per



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram  
Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

### TECHNICAL SPECIFICATION

#### Border meter

Doc. #: **SCM-SPEC/XD/EM**

Rev.#: 0

Effective Date 10.12.2021

clause 4.2.2.4.2 of CBIP Manual on standardization of AC static Electrical Energy Meters and shall be sealable independently to prevent unauthorized tampering. The terminal cover of the meter shall be fully covered. Sealing provision shall be made against opening of the terminal cover. It is necessary to provide screws with two holes for sealing purpose.

- 6.8.2.7 The terminals in the terminal block shall be of long socket type for connection of cables with copper conductors. Double screw arrangement shall be provided to achieve adequate termination. All terminals and connecting screws and washers shall be of tinned/nickel plated brass material.
- 6.8.2.8 The terminal screws shall have size not less than M –4. All terminals and connecting screws should be of Nickel plated brass materials.
- 6.8.2.9 The screw shall not have pointed end of threads. The ends of screws shall be such as not to pierce and cut the conductor used. The internal diameter of terminal hole should be 5.5 mm minimum and 8 mm maximum. The holes in the insulating material which form an extension of the terminal holes shall be sufficient in size to accommodate the insulation of 4mm<sup>2</sup> copper conductors.
- 6.8.2.10 The terminal cover shall be transparent with minimum thickness **2** mm and the material shall be same as that of meter case. It shall be of extended type and accommodate, in addition to the terminal block, a suitable length of external cable along with its insulation and suitable for wiring from the rear end of the meter board.
- 6.8.2.11 The fixing screws used on terminal cover for fixing and sealing shall be held captive in the terminal cover. When the meter is mounted on the meter board, no access shall be possible to the terminals without breaking the seals of the terminal. It is necessary to provide screws with two holes for sealing purpose.
- 6.8.2.12 The terminal block, terminal cover and meter case shall fulfill the test conditions for heat and fire resistance
- 6.8.2.13 The clearance and creepage distance of the terminal block and those between the terminals and the surrounding parts shall not be less than 3 mm. Clearance of minimum 3 mm shall be provided between the incoming and outgoing terminals.

#### 6.8.3 Sealing Arrangement

- 6.8.3.1 The Manufacturer shall put one seals ensuring traceability on left or right side of the meter top cover before dispatch. Polycarbonate or acrylic or holographic seals shall be used. Lead seals are not permitted at all. Provision for sealing by the utility shall also be there.
- 6.8.3.2 The seals should have serial numbers. A soft copy (in spread sheet compatible with open office calc/ Microsoft excel) of the No. of the seal against the sl. No. of each meter should be submitted to the consignee along with each lot of supply.
- 6.8.3.3 Terminal block (Meter Terminal Cover) shall be provided with separate sealing facility (at least two seals) which can be used by testing /commercial group of power utility as follows (a) One seal at left bottom (b) Next seal at right bottom. The manufacturer shall supply three other seals for (a) sealing meter top cover with meter body left/right (b) optical port and (c) MD reset button. The seals shall have KSEBL logo on one side and serial number with bar code, on the other side. The seals provided by the manufacturer at factory shall be preferably a coloured one from manufacturer for better identification or transparent and three seals supplied extra shall be colourless
- 6.8.3.4 The polycarbonate seals (to be used by the utility) to be provided along with each meter packet.

#### 6.8.4 Real Time Clock

- 6.8.4.1 The real time quartz clock (RTC) shall only be used in the meter for maintaining time (IST) and calendar. The time accuracy shall be as per provision of CBIP 325. Facility for adjustment of real time should be provided through CMRI with proper security
- 6.8.4.2 RTC shall be pre-programmed for 20 Years Day / date without any necessity for correction. Maximum



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

### TECHNICAL SPECIFICATION

Border meter

Doc. #: **SCM-SPEC/XD/EM**

Rev.#: 0

Effective Date 10.12.2021

drift shall not exceed +/- 3 Min/year.

- 6.8.4.3 The uncertainty of setting initial time shall not be more than  $\pm 30$  seconds from Indian Standard Time as maintained by NPL, New Delhi.
- 6.8.4.4 The RTC shall have long life (**10** Years) non-rechargeable battery.
- 6.8.4.5 Time & date setting shall only be possible through Common Meter Reading Instrument (CMRI), lap top or base computer.
- 6.8.4.6 Synchronization of Energy Meter 'RTC' Time/Date shall be possible through password/Key code enabled command from CMRI and Laptop. Security key /password required for enabling transaction like RTC, MD reset, profile capture period shall be made available to KSEBL. There shall be provision for online synchronization of RTC through optical port and RS 232 communication port.
- 6.8.4.7 The RTC battery and battery for display in the case of power failure shall be separate.

#### 6.8.5 Testing on Site

- 6.8.5.1 The meter shall be provided with separate flashing LED's for active and reactive energy to represent the pulse output for testing the meter by suitable testing equipment. The operation indicator must be visible from the front.
- 6.8.5.2 It shall be possible to check the accuracy of active/ reactive energy measurement of the meter on site by means of LED output. Resolution of the test shall be sufficient to enable the starting current test in less than 10 minutes and accuracy test at the lowest load shall be completed with desired accuracy within 5 minutes.

#### 6.8.6 Display of measured values.

- 6.8.6.1 The push button shall be provided for manual scroll mode and it should be easily accessible from the front side of the meter body when the meter is installed. It should be possible to scroll Up and Down using pushbuttons. The display should be programmed in such a way that it should go to the sleep mode only after a certain time. Separate push buttons for upward and downward scrolling is desirable. However single push button is acceptable if both function can be achieved easily
- 6.8.6.2 The meter shall have 7 digits with '-' sign to indicate negative parameter identifier and Backlit Liquid Crystal Display (LCD). *(The absence of a prefix sign itself indicates positive sign and hence separate positive sign is not required.)* The size of digit should be minimum 10x5mm. The Dot Matrix type LCD is not acceptable. Display legend shall be readable. Backlit with sufficient brightness to view the readings in the day light shall be provided for the display. Display parameters shall be displayed in the same window and shall not toggle in the display.
- 6.8.6.3 LCD shall be suitable for temperature withstands of 80<sup>0</sup> C (storage) and 70<sup>0</sup> C (operation).
- 6.8.6.4 The meter should have a nonvolatile memory, so that the registered parameters will not be affected by the loss of power. The non-volatile memory shall have a minimum retention time of 10 years.
- 6.8.6.5 While displaying zone wise related parameters, proper display indication may be provided for identifying the zones.
- 6.8.6.6 Power flow from Mains (M) to Load (L) shall be assigned as forward or import and power flow from Load to Mains is Reverse/Export.
- 6.8.6.7 deleted
- 6.8.6.8 Selective parameters from the Auto Mode like Billing Energy Import and Export kWh, Present Energy Import and Export kWh, Demand, Power Factor, Reset count should only be available in the Battery Mode.



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram  
Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

### TECHNICAL SPECIFICATION

Border meter

Doc. #: SCM-SPEC/XD/EM

Rev.#: 0

Effective Date 10.12.2021

#### 6.8.6.9 Following measuring parameters should be displayed:

##### Auto Scroll Mode

Auto Scroll Parameters shall be rolled over every 10 seconds each

1. Self Diagnostic
2. Meter Sl.No
3. LCD segment check
4. Real Date and Time
5. Instantaneous R phase Voltage (Phase to neutral)
6. Instantaneous Y phase Voltage (Phase to neutral)
7. Instantaneous B phase Voltage (Phase to neutral)
8. Deleted.
9. Instantaneous current R phase
10. Instantaneous current Y phase
11. Instantaneous current B phase
12. Frequency
13. Instantaneous Signed PF (Import & Export)
14. Phase sequence voltage & current (in single or consecutive Display)
15. Instantaneous Signed Apparent Power in KVA (Import & Export)
16. Instantaneous signed Active Power in kW (Import & Export)
17. Cumulative kWh (Import)
18. Cumulative kWh Zone 1(Import)
19. Cumulative kWh Zone 2(Import)
20. Cumulative kWh Zone 3(Import)
21. Cumulative kWh (Export)
22. Cumulative kWh Zone 1(Export)
23. Cumulative kWh Zone 2(Export)
24. Cumulative kWh Zone 3(Export)
25. Cumulative kVAh (Import)
26. Cumulative kVAh Zone 1 (Import)
27. Cumulative kVAh Zone 2 (Import)
28. Cumulative kVAh Zone 3 (Import)
29. Cumulative kVAh (Export)
30. Cumulative kVAh Zone 1 (Export)
31. Cumulative kVAh Zone 2 (Export)
32. Cumulative kVAh Zone 3 ( Export)
33. Current Maximum Demand in kVA (Import)
34. Current Maximum Demand in KVA Zone 1 (Import)
35. Current Maximum Demand in KVA Zone 2 (Import)
36. Current Maximum Demand in KVA Zone 3 (Import)
37. Current Maximum Demand in KVA (Export)
38. Current Maximum Demand in KVA Zone 1 (Export)
39. Current Maximum Demand in KVA Zone 2 (Export)
40. Current Maximum Demand in KVA Zone 3 (Export)
41. Net Active Energy (Import-Export)
42. History 1 –Cumulative Kwh (Import)
43. History 1 –Cumulative Kwh Zone 1 (Import)
44. History 1 –Cumulative Kwh Zone 2 (Import)
45. History 1 –Cumulative Kwh Zone 3 (Import)
46. History 1 – Cumulative KVArh lag (Import)
47. History 1-Cumulative KVArh lead (Import)



# SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram  
Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

## TECHNICAL SPECIFICATION

### Border meter

Doc. #: **SCM-SPEC/XD/EM**

Rev.#: 0

Effective Date 10.12.2021

48. History 1- Cumulative KVAh (Import)
49. History1- Cumulative KVAh Zone 1 (Import)
50. History 1-Cumulative KVAh Zone 2 (Import)
51. History 1-Cumulative KVAh Zone 3 (Import)
52. History 1 –Cumulative Kwh (Export)
53. History 1 –Cumulative Kwh Zone 1 (Export)
54. History 1 –Cumulative Kwh Zone 2 (Export)
55. History 1 –Cumulative Kwh Zone 3 (Export)
56. History 1- Cumulative KVArh lag (Export)
57. History 1-Cumulative KVArh lead ( Export)
58. History 1-Cumulative KVAh (Export)
59. History 1-Cumulative KVAh Zone 1 (Export)
60. History 1-Cumulative KVAh Zone 2 (Export)
61. History 1-Cumulative KVAh Zone 3 (Export)
62. History 1-Net active Energy (Import – Export)
63. Deleted.
64. History 1 Maximum Demand in KVA (Import)
65. History 1 Maximum Demand in KVA Zone 1 (Import)
66. History 1 Maximum Demand in KVA Zone 2 (Import)
67. History 1 Maximum Demand in KVA Zone 3(Import)
68. History 1 Maximum Demand in KVA (Export)
69. History 1 Maximum Demand in KVA Zone 1 (Export)
70. History 1 Maximum Demand in KVA Zone 2 (Export)
71. History 1 Maximum Demand in KVA Zone 3 (Export)
72. CMD in KVA (Import)
73. CMD in KVA (Export)
74. MD reset count
75. Programmed CT Ratio
76. Programmed PT Ratio (shall be programmed as 100)
77. Cumulative Program Count
78. Date and Time of Last Reset
79. Cumulative Power OFF Duration
80. Cumulative Tamper Count
81. Present Status of abnormality

### **Push Button Mode**

All display parameters in Auto Scroll Mode shall be provided in this page

### **High Resolution Mode(2+5 digits) (Page 3)**

1. High Resolution Display Cumulative kWh (Import)
2. High Resolution Display Cumulative kVArh Lag (Import)
3. High Resolution Display Cumulative kVArh Lead (Import)
4. High Resolution Display Cumulative kVAh (Import)
5. High Resolution Display Cumulative kWh (Export)



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram  
Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

### TECHNICAL SPECIFICATION

#### Border meter

Doc. #: **SCM-SPEC/XD/EM**

Rev.#: 0

Effective Date 10.12.2021

6. High Resolution Display Cumulative kVArh Lag (Export)
7. High Resolution Display Cumulative kVArh Lead (Export)
8. High Resolution Display Cumulative kVAh (Export)

Note : All Parameters shall be downloadable for analysis.

- 6.8.6.10 The meter body shall be type tested for IP51 degree of protection as per IS 12063 against ingress of dust, moisture & vermin. Dust proof window of transparent material (toughened) glass or UV stabilized poly carbonate ) shall be provided to permit a clear view of the display. The fixing arrangement shall be such that the window glass cannot be removed without breaking the seal.
- 6.8.6.11 The maximum demand shall automatically be reset at 24.00 hours of the last day of each calendar month. Manual reset push button shall be provided to reset the meter at any time by the utility personnel. A minimum delay equal to demand integration period set between two successive manual resets is desirable. There shall be provision for sealing the manual reset push button. Facility shall be provided for remote MD reset from base station computer with password protection.
- 6.8.6.12 Integration period for kVA /kW maximum demand shall be of 30minutes real time based. Provision shall be there to change the integration time for MD to 15 minutes, if required through CMRI and laptop with password.
- 6.8.6.13 The meter shall be supplied with battery backup feature for displaying the parameters during power OFF condition. Battery life shall be minimum ten years. Battery backup shall be provided internally. While taking reading in battery mode, the battery push button need not be pressed continuously. The meter should continue in battery mode while taking reading using UP/DOWN scroll key. Once the push button is released, the parameter shall be displayed for a sufficient duration for taking readings without any interruption.
- 6.8.6.14 kWh, kVArh and kVAh for both import and export should have high resolution display to facilitate testing with desired accuracy within reasonable time. It shall be possible to read these high resolution values using CMRI.
- 6.8.6.15 Manual scroll mode shall be selectable from any point during the auto scroll mode. If no manual keys are pressed for 2 minutes the display shall automatically returns to auto scroll mode.

#### 6.8.7 Anti tamper Features

- 6.8.7.1 The meter shall detect and register the active and reactive energy correctly in both direction under Change of phase sequence ( voltage and current ) condition.
- 6.8.7.2 The meter should work accurately even without neutral.
- 6.8.7.3 The meter should work in the absence of any one or two phases. It should show the readings accurately for the phases having connection.
- 6.8.7.4 All the above tampers will be verified at basic current at reference voltage.
- 6.8.7.5 The potential link shall not be provided on terminal block outside the main meter cover.
- 6.8.7.6 Visual indication shall be provided to show tamper conditions stated above.
- 6.8.7.7 The meter shall comply all the test for external AC/DC magnetic field as per CBIP PUB No. 325. Moreover, the magnetic influence test for permanent magnet of 0.5 T for minimum period of 15 minutes shall be carried out, by putting the magnet on the meter body. After removal of magnet, meter shall be subjected to accuracy test as per IS14697/1999(amended up to date).
- 6.8.7.8 In the event the meter is forcibly opened, even by 2mm displacement of the meter cover, same



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram  
Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

### TECHNICAL SPECIFICATION

#### Border meter

Doc. #: SCM-SPEC/XD/EM

Rev.#: 0

Effective Date 10.12.2021

should be recorded as tamper event with date & time stamping and the meter should continuously display that the cover has been tampered. This display shall toggle with the normal display parameter.

#### 6.8.8 Self-diagnostic Tests

6.8.8.1 The meter shall be capable of performing complete self-diagnostic check to monitor the circuits for any malfunctioning to ensure integrity of data memory location at all time. The meter shall have indication for unsatisfactory/non-functioning/malfunctioning of the following:

- a. Time and date on meter display
- b. All display segments( all alpha numeric) on meter display
- c. Battery
- d. Self diagnostic (RTC, NVM information) on display

6.8.8.2 All display segments: "LCD Test" display shall be provided for this purpose.

### 7 OPERATIONAL REQUIREMENTS

#### Abnormality of Events

The meter should have features to detect the occurrence and restoration of the following abnormal events:

#### 1. Missing potential and potential imbalance

The meter shall be capable of detecting and recording occurrence and restoration with date and time the cases of potential failure (one phase or two phases) and low potential, which could happen due to disconnection of potential leads (one or two), even at zero current. Meter shall also detect and log cases of voltage unbalance (20% or more for 3 Minutes.) Higher of the 3 phase voltages shall be considered as reference for this purpose. The meter shall log as missing potential event if the respective voltage is  $<70\%$  of  $V_{ref}$ .

#### 2. Neutral Disturbance

Meter shall record the event when any phase voltage is more than 120% of  $V_{ref}$ . Meter shall immune to DC voltage disturbance of 400V.

#### 3. Current unbalance:

The meter shall be capable of detecting and recording occurrence and restoration with date and time of current unbalance (30% or more for 3 minutes).Higher of the 3 phase currents shall be considered as reference for this purpose.

#### 4. Power OFF

The meter shall be capable to record power OFF events in the meter memory. For this, the meter



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram  
Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

### TECHNICAL SPECIFICATION

#### Border meter

Doc. #: **SCM-SPEC/XD/EM**

Rev.#: 0

Effective Date 10.12.2021

shall keep records for minimum 125 events (Occurrence +Restoration).

#### 5. Current Missing

The meter shall be capable of detecting and recording occurrences and restoration of current missing in any one or two phases of current, with date & time of occurrence and restoration if the respective phase current falls below 1% of  $I_b$ .

#### 6. External Magnetic Influence

The performance of meter shall not be affected under the influence of external DC/AC and permanent magnetic field of high intensity as mentioned in CBIP 325 and record the influence of abnormal magnetic field with date and time in the memory. The event shall also displayed in the auto mode.

#### 7. Wrong phase association indication on display

Display of proper indication shall be shown in case of wrong phase association.

**8.** The persistence and restoration time for tamper logging shall be 3 minutes and 2 minutes respectively.

**9.** The metering system shall be provided with adequate magnetic shielding so that any external magnetic field (AC electro magnet or DC magnet ) applied on the metering system shall not affect the proper functioning and recording of energy as per error limits prescribed by CBIP Guide 325.

**10.** The meter shall keep records for the minimum 500 events of abnormality (occurrence + restoration). For above abnormal conditions, the recording of events shall be on FIFO basis. It shall be possible to retrieve the abnormal event data along with all related snap shots data through the meter optical port with the help of CMRI & downloaded the same to the base computer. All the information shall be made available in simple & easy to understand format compartmentalized as follows.

Compartment No.1 150 events of potential related

Compartment No.2 150 events of current related

Compartment No.3 50 other events

Compartment No.4 125 events of power failure

Compartment No.5 24 events of transaction related changes

Compartment No.6 1 event of cover open

The tamper which has occurred earlier and not yet restored shall be logged in a separate register and to be shown in the downloaded meter data.(optional)





## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

### TECHNICAL SPECIFICATION

Border meter

Doc. #: SCM-SPEC/XD/EM

Rev.#: 0

Effective Date 10.12.2021

#### 8 Connection Diagram and Terminal Marking

8.1. Every meter shall be indelibly marked with a connection diagram showing the phase sequence for which it is intended and shall be clearly shown on the inside portion of the terminal cover and shall be of permanent nature. In case any special precautions need be taken at the time of testing the meter, the same may be indicated along with the circuit diagram.

8.2. Meter terminals shall also be marked and this marking should appear in the above diagram.

8.3. Stickers of any kind will not be accepted in this regard.

#### 9 NAME PLATE DETAILS

9.1 Every meter shall have a name plate clearly visible and indelible and distinctly marked in accordance with relevant standards. The following information shall appear on a nameplate inside the meter.

1. Manufacturer's name & trade-mark and place of manufacture.

2. Serial number.

3. Designation of type.

4. Number of phases and number of wires for which the meter is suitable.

5. Guarantee period.

6. Purchaser's name

7. Purchase Order No.

8. Principal unit in which the meter records.

9. Reference voltage & frequency in Hz.

10. Basic current and rated maximum current .

11. Meter constant (pulse rate of testing signal).

12. Reference Temperature

13. Class index.

14. Month and Year of manufacture

15. BIS marking as per statutory requirement

16. CT Ratio

17. PT Ratio



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

### TECHNICAL SPECIFICATION

Border meter

Doc. #: **SCM-SPEC/XD/EM**

Rev.#: 0

Effective Date 10.12.2021

18.Border Meter (Bi-directional)

19.DLMS Compliant Category B Meter

20.Sign of double square for encased meters of protective class II

21.Firm ware version of the meter.

9.2 The Meter Serial No. shall be Bar Coded along with numeric No. The size of Bar Code shall not be more than 35 X 5 mm.

9.3 Stickers in any case will be not accepted for name plates

#### 10 DATA COMMUNICATION FACILITIES

10.1 Data architecture and communication protocols shall enable easy multi-vendor exchange of data without usage of any converting/translating equipment. For this, the data structure adopted within the energy meter shall be on an internationally acceptable method. The data structure/coding details shall be furnished to the Owner. All necessary software required for down loading the information to a user friendly Windows'/LINUX based operating system of Base billing computer system through CMRI shall be furnished in required number of copies (On CD) without any additional cost to the purchaser.

10.2 The data transfer shall be highly reliable and fraud proof (No editing shall be possible on base computer by any means).The software shall have capability to convert all the data into ASCII format.

10.3 Energy meter shall have a galvanically isolated optical communication port with proper cover & sealing facility in front of the meter for data transfer to or from a hand held CMRI and LAPTOP and another port for remote reading and both the ports conforming to IEC62056-21) as per below details.

10.4

##### a) LOCAL COMMUNICATION PORT

The energy meter shall have a galvanically isolated IEC 1107 optical communication port with proper cover & sealing facility located in front of the meter for data transfer to or from a hand held Data Collection Device. This port shall also be used for remote data reading through modem. Sealing provision should be available for optical port. It shall be possible to download the data through CMRI on power off condition and such that the battery shall be of adequate capacity.

b) **REMOTE COMMUNICATION PORT** Meter shall have an additional communication port (RS 232) in the form of RJ11 port to interface external modem for remote data collection through VSAT/PSTN/optical fiber/ GSM/GPRS/CDMA/PLCC/LPR communication modem. RS 232 (RJ11) port shall be preferably located under the terminal cover.

Both the ports will support communication on DLMS and should be accessible through a DLMS compliant HHU. Provisions for sealing both the ports are to be made available.



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

### TECHNICAL SPECIFICATION

Border meter

Doc. #: SCM-SPEC/XD/EM

Rev.#: 0

Effective Date 10.12.2021

10.5

#### METER READING DURING POWER OFF

It should be possible to read the meter display visually and with MRI in absence of input voltages with help of battery backup.

#### DATA DOWNLOADING CAPABILITIES

Meter shall support a minimum baud rate of 9600 on optical port. It shall be possible to read selective data from the meter as specified in the companion standard.

#### 11 LOAD SURVEY

Block load survey parameters shall be provided as per table 25 (clauses D-2 and D-4.3) of IS 15959 2011 and its latest amendments

11.1 Load survey parameters shall be available for minimum 90 days.

11.2 The logging interval for load survey shall be 30 minutes. Load survey data shall be logged for the last 90 days on time basis. This load survey data can be retrieved using CMRI/Laptop/ any suitable equipment as and when desired and load profiles shall be viewed graphically and analytically with the help of meter application software. Whenever meter is taken out and brought to laboratory, the Load Survey data shall be retained for the period of actual use of meter. The meter application software shall be capable of exporting / transmitting these data for analysis to other user software in spreadsheet format.

11.3 The resolution for load survey parameters shall be 0.01 kWh

11.4 Billing History:

The meter shall record the history of billing parameters, Cumulative kWh, Cumulative kVarh lag, cumulative kVarh lead, Cumulative kVAh and kVA MD at the time of reset for both import and export for last 12 months.

11.5 DAILY LOAD SURVEY

Daily load survey parameters shall be provided as per table 26 (clauses D-2 and D-5.1) of IS 15959 and its latest amendments.

11.6 TREND

The downloaded meter data shall be able to construct trend during the load survey period as listed below.

1. Energy (import & export)

2. Voltage (R,Y,B)

3. Current (R,Y,B)

4. P.F

5. Demand(import & export)

11.7 All data downloaded shall be easily convertible to printable format and be able to save as pdf.



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

### TECHNICAL SPECIFICATION

Border meter

Doc. #: SCM-SPEC/XD/EM

Rev.#: 0

Effective Date 10.12.2021

11.8 The number of pages in the report should be minimum and shall cover all the details mentioned above.

#### 12 Tests

12.1 The meter shall be tested with its base and cover in position; all parts intended to be earthed shall be earthed.

12.2 Before any test is made, the circuits shall have been energised for a time sufficient to reach thermal stability but not less than one hour.

12.3 The connection shall be done as marked on the diagram of connections

12.4 All tests are to be carried out under reference conditions as specified in IS 14697/1999 unless otherwise specified-

12.5 During the tests for accuracy requirements, proper repeatability conditions shall be maintained. During type tests, repeatability at any test point determined on the basis of three readings at short intervals, shall be better than 1/5<sup>th</sup> of the limit of percentage error under reference conditions. Manufacturer shall state the necessary number of pulses/ pulse counts for maintaining the repeatability condition.

12.6 Uncertainty of measurement of percentage error shall not exceed 1/5<sup>th</sup> of the limit of percentage error for the given test point at reference conditions. If the uncertainty exceeds this limit, all the limits of percentage errors shall be reduced as described in CBIP 'manual on standardization of AC static energy meters' to make allowances for such uncertainty.

12.7 Unless otherwise specified, procedure for carrying out tests and the results of those tests shall conform to the relevant clause in Manual on Standardization of AC Static Electrical Energy Meters, Pub. No. 325, CBIP, July 2008 and if it is not mentioned in the above manual, then to IS 14697/1999 (amended up to date) or CBIP Tech-Report 88 with latest amendments.

#### 12.8 Type Tests

12.8.1 Meter shall be fully type tested as per IS 14697/1999 (amended up to date), Manual on Standardization of AC Static Electrical Energy Meters, Pub. No. 325, CBIP, July 2008 and CBIP Tech-Report 88 with latest amendments

12.8.2 Requirement of results and the procedure for conducting tests which are not specifically mentioned in this document shall be same as that mentioned in the Manual on Standardization of AC Static Electrical Energy Meters, Pub.No. 325.

12.8.3 The Type Test Reports shall clearly indicate the design and constructional features of the type tested meters.

12.8.4 Separate Type Test Reports for each offered type of meters shall be submitted.

12.8.5 All the Type Tests shall have been carried out from Laboratories such as CPRI, ERDA, ERTL (East) or equally reputed and accredited by the National Board of Testing and Calibration Laboratories (NABL) of Govt. of India to prove that the meters meet the requirements of the specification.

12.8.6 Type Test Reports conducted in manufacturers own laboratory and certified by testing institute shall not be acceptable.

12.8.7 Type test certificates rather than type test reports are preferred.

12.8.8 Type test certificate/ reports shall be submitted along with the offer and the same shall not be more than 24 months old on the date of tender. If the type test certificate/ reports are not within the valid period, the offer shall be rejected.

12.8.9 In case the test certificate / reports partially is/ are not meeting the requirement tests are to be carried out at no extra cost in owners presence. The same should be assured at the time of bidding.



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

### TECHNICAL SPECIFICATION

Border meter

Doc. #: SCM-SPEC/XD/EM

Rev.#: 0

Effective Date 10.12.2021

### 13 Routine and Acceptance Tests

a. Meters shall pass the entire acceptance and routine tests, as laid down under IS 14697 and also additional acceptance tests as prescribed in this specification.

b. Following routine tests are to be conducted on every product:

- 1.AC Voltage Test
- 2.Insulation Resistance Test
- 3.Test on limits of error
- 4.Test of meter constant
- 5.Test of starting condition
- 6.Test of no load condition

An acceptance test shall be carried out under the reference voltage, rated frequency and  $\text{Cos } \Phi$  ( $\text{Sin } \Phi$ ) = 1 for active (reactive) energy meter sat 5% of rated current. Six error tests are to be carried out successively in the load condition at intervals of 5 minutes. The variation in meter error expressed by the difference between the maximum and minimum of the errors so obtained in all these error tests shall not exceed the value corresponding to  $1/5^{\text{th}}$  of the limit of percentage error at the test points.

c. Following acceptance tests are to be carried out selected samples from a lot:

1. AC Voltage Test
2. Insulation Resistance Test
3. Test on limits of error
4. Test of meter constant
5. Test of starting condition
6. Test of no load condition
7. Repeatability of error test
8. Test of power consumption

d. Other acceptance tests

i) Tamper conditions as stated in this specification

ii) Glow wire testing for poly carbonate material

iii) The meter shall comply all the test for external AC/DC magnetic field as per CBIP PUB No.325 with latest amendments, moreover, the magnetic influence test for permanent magnet of 0.5T for minimum period of 15 minutes shall be carried out, by putting the magnet on the meter body. After removal of magnet, meter shall be subjected to accuracy test as per IS 14697/1999(amended up to date).

iv) The meter shall withstand impulse voltage at 10 kV peak and impulse voltage test is to be carried out on selected samples.



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

### TECHNICAL SPECIFICATION

#### Border meter

Doc. #: **SCM-SPEC/XD/EM**

Rev.#: 0

Effective Date 10.12.2021

v) Vibration test

vi) Fully assembled and finished meter shall undergo burn in test process for 12 hrs at 55 °C (maximum temperature not to exceed 60 °C under base current ( $I_b$ ) load condition.

vii) KSEBL has a meter data acquisition software (MDAS) currently running in Linux (CentOS release 6.4) platform, which is already acquiring the meter data of different DLMS meters currently installed in KSEBL. Sample meter/modem of bidders would be tested using this MDAS application of KSEBL, regarding

- a. Communication of meter data on pre defined frequency as well as "on-demand basis" (instantaneous parameters, billing parameters etc.)
- b. MD rest/time synchronisation from MDAS application. All the required software components for receiving meter data and converting this meter data into CDF formats will have to be provided by the bidders.

### 13.1 Normal Sampling Plan

For acceptance test, meters shall be selected at random from the lot, depending upon the size of the lot and the desired acceptance quantity level.

(a) No load condition & starting condition:- While accepting the meters the number of sample meters will be taken out from the lot for testing ( lot means the total number of meters received in a Store out of inspected and approved lot by purchaser's representative under one approval letter) depending upon the size of the lot and will be taken random from the lot in accordance with the following table.

#### Lot size Number of meters to be selected at random

Upto 300 8

301 to 500 13

501 to 1000 20

1001 and above 32

Selection of number of sample meters by the consignee per lot for testing is subject to vary as per the latest IS on sampling.

If the number of defectives found in the sample of 32 is less than or equal to 1, the lot will be considered. If the number of defectives is greater than or equal to 4, the lot will be rejected. If the number of defective is 2 or 3 a further sample of 32 meters will be taken and subjected to the tests. If the number of defectives in two samples combined is less than 4, the lot will be considered as conforming to the tests, otherwise rejected.

(b) Tests of insulation resistance, Ac voltage test, Test of power consumption:-

Tests of insulation resistance, AC voltage test, Test of power consumption, test of meter



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

### TECHNICAL SPECIFICATION

Border meter

Doc. #: **SCM-SPEC/XD/EM**

Rev.#: 0

Effective Date 10.12.2021

constant/registration, limits of error and interpretation of test results and adjustment.

From the sample of meters which have been drawn according to above clause 'a' and those that have passed all test of a sample of 8 meters shall be tested, all of which shall pass for conformity to these tests. If any one of the meters fails the whole lot shall be declared not conforming to the requirements of these tests.

(c) Test of repeatability of Error:- Above tests shall be carried out on 3 samples selected from above meters under clause 'b' and shall be tested for repeatability of error test separately. If any one of the meters fails the whole lot shall be declared not conforming to the requirement of these tests.

### 13.2 Pre dispatch Inspection

- 13.2.1 All Acceptance tests and Inspection shall be carried out at the place of manufacturer unless otherwise specially agreed upon by the manufacturer and purchaser at the time of purchase.
- 13.2.2 The manufacturer shall offer to the inspector representing the purchaser, all the reasonable facilities, free of charge, for inspection and testing, to satisfy him that the material is being supplied in accordance with this specification. Company's representative(s) / Engineer(s) attending the above testing will carry out testing on suitable number of meters as per sampling procedure mentioned in this document and additional acceptance test as per this specification on samples and issue test certificate approval to the manufacturer and give clearance for dispatch.
- 13.2.3 All the meters offered for inspection shall be in sealed condition. The seals of sample meters taken for testing & inspection will be opened & resealed after inspection.
- 13.2.4 KSEB have the right to ask the supplier to furnish new type tests certificates of sample meters at suppliers cost ,at any time after the completing supply of 50% of the ordered quantity .The sample for these tests will be selected from the quantity meters already supplied. If the selected meters fail in type tests KSEB have the right to cancel the purchase order.

### 13.3 Inspection after Receipts at Store

- 13.3.1 While accepting the meters at TMR Divisions, the number of sample meters will be taken out from the lot for testing, depending upon the size of the lot and will be taken at random from the lot in accordance with sampling plan given in clause 13.1. If the sample/s selected, does not conform to the tests, lot will be rejected and no compensation will be given.

Physical verification:- The sample meters shall be verified for conformity of physical requirements such as RTC fail, push button fail, tamper indications, display fail, discrepancy in display, pulse fail, battery back ups, damaged body/ cover / terminal cover, non matching screws and threads, improper holes in sealing screws etc.

### 13.3.2 No: of resubmission & rejection at each TMR .

The supplier shall be permitted to replace rejected lot only once in each lot in each TMR. Further rejection of replaced quantity will lead to deduction of the same quantity from the purchase order quantity If the total deducted quantity is more than 20% of the ordered quantity, the KSE Board reserves the right to cancel the purchase order and to blacklist the firm.

## 14 Guarantee

- 14.1 The Three Phase, four wire, HT, CT/PT operated meters with LCD and ToD facility should be guaranteed for a minimum period of **five years** from the date of acceptance.
- 14.2 The meter should have a design life not less than ten years.



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram  
Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

### TECHNICAL SPECIFICATION

#### Border meter

Doc. #: **SCM-SPEC/XD/EM**

Rev.#: 0

Effective Date 10.12.2021

- 14.3 The meter found defective within the above guarantee period shall be replaced by the supplier free of cost, within three months from the date of receipt of intimation. The intimation shall be either by hand or by registered post / courier with proper acknowledgement.
- 14.4 If defective meters are not replaced within the specified period as above, the Board shall recover an amount equivalent to the cost of meter plus 15% supervision charges from any of the bills of the supplier. The amount so deducted will be refunded once the faulty meter is replaced after deducting the supervision charges.
- 14.5 At any case the overall failure rate of meter should not be more than 2.5% of the Quantity supplied.

### 15 Quality Control

The purchaser has a right to send a team of experienced engineers for assessing the progress of manufacturing and quality at any time .The team should be given all assistance and co-operation for inspection and testing at the bidder's works.

### 16 Component Specification

Sl. No	Component Function	Requirement	Makes
1	Measurement or computing chips	The measurement or computing chips used in the Meter should be with the Surface mount type.	USA: Analog Devices, Cyrus Logic, Atmel, Philips, Dallas, ST, Renesas Silergy (Maxim Integrated) Germany: Siemens Texas, Japan : NEC Freescale
2	Memory chips	The memory chips should not be affected by external parameters like sparking, high voltage spikes or electrostatic discharges. Meter shall have non volatile memory (NVM). No other type of memory shall be used for data recording and programming. (The life of the NVM is highest) There shall be security isolation between metering circuit, communication circuit, and power circuit.	USA: Atmel, National Semiconductors, Texas Instruments, Philips, ST, Japan : Hitachi Germany: Siemens Rohm, Micron
3	Display modules	a) The display modules should be well protected from the external UV radiations.  b) The display visibility should be sufficient to read the Meter mounted at height of 0.5 to 2m from ground level (refer 3.2 d for Viewing angle). The LCD and ToD facility display should have wide viewing angle of 45 degree to 60 degree cone up to 1m distance	Japan : Hitachi, Sony, L&G, Haijing Tinma (China) TEXAS ,Yeboo, Truly Semiconductor





## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram  
Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

### TECHNICAL SPECIFICATION

#### Border meter

Doc. #: **SCM-SPEC/XD/EM**

Rev.#: 0

Effective Date 10.12.2021

		<p>c) The construction of the modules should be such that the displayed quantity should not disturbed with the life of display (PIN Type).</p> <p>d) It should be trans-reflective HTN (HTN – Hyper Twisted Nematic (120°)) or STN (STN – Super Twisted Nematic (160°)) type industrial grade with extended temperature range.</p> <p>HTN – Hyper Twisted Nematic (120°)</p> <p>STN – Super Twisted Nematic (160°)</p>	
4	Electronic components	The active & passive components should be of the surface mount type & are to be handled & soldered by the state of art assembly processes.	<p>USA : National Semiconductors, Atmel, Philips, Texas Instruments, BC Component</p> <p>Japan : Hitachi, Oki, AVZ</p> <p>Samsung</p> <p>Japan : Panasonic</p> <p>Germany : Vishay</p> <p>NXP, Yageo, Epcos AVX</p>
5	Battery	Only non rechargeable battery should be used for RTC and for display both rechargeable and non rechargeable battery may be used. The RTC battery and battery for display in the case of power failure should be separate.	<p>USA : Maxell</p> <p>Japan,Indonesia : Panasonic,Sony,</p> <p>Germany : Varta</p> <p>France : Saft</p> <p>Elegance</p> <p>Vitzro</p> <p>Tekcell</p> <p>XENO.EVE,Eternacell,Mitsubishi</p>

Sd/-

**Chief Engineer (SCM)**



# SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram  
Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

## TECHNICAL SPECIFICATION

Border meter

Doc. #: SCM-SPEC/XD/EM

Rev.#: 0

Effective Date 10.12.2021

### GUARANTEED TECHNICAL PARTICULARS

**Three Phase,4 Wire,-/5A 11kV/63.5 V 0.5 S, HT CT/PT operated static, bi-directional meter for border metering.**

SI.No	PARTICULARS	VALUES
1	Type / Model	
2	Standard/s to which the meter conforms	IS 14697, CBIP 325, IS 15959
3	Guarantee Period	5 years from the date of acceptance of the final lot
4	Rated Voltage:	63.5 V (P-N)
5	Basic Current(Ib):	5 A
6	Maximum Current(Imax)	10 A
7	Frequency Range:	50 Hz +/- 5%
8	Power Factor Range	0 lag- unity- 0 lead
9	ISI mark	Yes complied
10	Minimum Starting Current	0.1% of Ib
11	Accuracy class for kWh and kVARh	0.5 S for both kWh and kVARh
12	Test Output device	Yes - left LED for kWh and right LED for kVARh.
13	Operation indicator	Yes
14	Power consumption in voltage and current circuit	As per technical offer (1W, 4VA for Voltage circuit, 1VA for current circuit)
15	Limits of error at all Power factor of unity/0.5 at multiples of rated currents	As per IS 14697
16	Change in error due to Variation in frequency Variation in Temperature Variation in Voltage Variation in current Due to single phase current	As per IS 14697 As per IS 14697 As per IS 14697 As per IS 14697 As per IS 14697
17	One minute Power frequency withstand Voltage	As per specification



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram  
Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

### TECHNICAL SPECIFICATION

#### Border meter

Doc. #: **SCM-SPEC/XD/EM**

Rev.#: 0

Effective Date 10.12.2021

18	Compliant to EMC & EMI	As per IS 14697
19	Basic insulation level: Impulse withstand Voltage	As per specification
20	Current rating of the terminal	As per specification
21	External Magnetic Influence	As per specification
22	Maximum size of cable, which can be connected at terminals	As per specification
23	Terminals to be bi-metallic and suitable for Aluminum / Copper Cables	As per specification
24	Maximum number of ToD zones that can be programmed and are programmed	As per specification
25	Integration period for MD that is programmed and can be programmed	15/30 min
26	Whether programming of ToD and MD integration period can be done in the field using CMRI or Laptop	Yes
27	If so, whether the facilities are having adequate security and if so, detail it.	As per specification
28	ToD wise kWh and kVAh	Yes, complied
29	Whether phase wise kVAR, KW & KVA, overall pf, MD reset count, frequency, time & date , RTC battery health parameters are available in data collection?	As per specification
30	Terminal Block material	As per specification
31	Material for meter base and cover and whether the cover is transparent	As per specification
32	Material for terminal cover and whether the cover is transparent	As per specification
33	Resistance to Heat and Fire	As per specification
34	Details of meter case	As per specification
35	Degree of protection against dust and water	IP 51
36	Details of alpha-numeric LCD display	As per specification
37	Display parameters available in auto scroll mode and display time of each parameter	As per specification



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram  
Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

### TECHNICAL SPECIFICATION

#### Border meter

Doc. #: **SCM-SPEC/XD/EM**

Rev.#: 0

Effective Date 10.12.2021

38	Display parameters available in manual scroll mode and display time of each parameter	As per specification
39	High resolution display parameters	Yes
40	No. of digits in the display	7 digits, 7 segment display
41	Tamper protection features	Yes
	Voltage failure	
	Current Unbalance	Yes
	Current bypass	Yes
	Magnetic Logging	Yes
	Any other	NA
42	Whether test output provided	Yes
43	Meter & Terminal Cover sealing	Yes
44	Date of issue of Type Test Certificate/report	
45	Issuing authority of type test certificate/ reports	
46	Whether any changes in design from that type tested	No
47	Whether all type tests were conducted and all are on same design	Yes
48	Whether meter is designed with ASIC or microcontroller	Yes
49	List of bought out items which are used in the manufacturing of the meter	As per specification
50	Standard followed in Assembly of electronic components	As per relevant standard
51	Suppliers of metering ICs and microcontrollers	As per specification
52	Whether the suppliers are STACK or IECQ registered suppliers	As per specification
53	State of art technology used in the manufacturing and assembly	As per specification
54	Provision for testing sub- assembled cards	As per specification
55	Details of volatile memory used	As per specification
56	Whether terminal cover is an extended transparent terminal cover	As per specification



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram  
Administered by TMRs | Kannur | Shoranur | Angamaly | Pallom | Thirumala

### TECHNICAL SPECIFICATION

#### Border meter

Doc. #: **SCM-SPEC/XD/EM**

Rev.#: 0

Effective Date 10.12.2021

57	Minimum clearance and creepage distance of the terminal block and those between the terminals and the surrounding parts	As per IS 14697
58	Whether RTC is pre-programmed	As per IS 14697
59	Life of RTC battery	10 years
60	Maximum drift of RTC per year	As per IS 14697
61	Way of synchronisation of Energy Meter and 'RTC'	As per specification.
62	Life of Battery for display parameters	As per offer 10 years
63	Whether meter terminals are marked	As per IS 14697
64	Connection diagram is provided and whether it is a sticker?	Yes Connection diagram is laser printed and then embossed on name plate
65	Name plate details and whether meter serial number and bar code is given in the name plate	Yes As per IS 14697
66	Meter base and cover jointing method	Ultrasonic welding
67	Method adopted to transform voltage and current to the desired low values	Through CT/PT ratio
68	Details of factory programmable parameters	As per specification
69	Details of user programmable parameters	As per specification
70	Data communication facilities	As per specification
71	Whether All necessary software for down loading the information through CMRI will be supplied without any additional cost?	As per specification and IS 15959
72	Whether Energy meter have a galvanically isolated optical communication port as per IEC 62056-21?	Yes

**Sd/-**  
**CHIEF ENGINEER (SCM)**