



---

# SUPPLY CHAIN MANAGEMENT

## THIRUVANANTHAPURAM

---

### SPECIFICATION

---

33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

APPLICABLE TO KSEBL	Rev#0	DOC. NO.: SCM-SPEC/XM/3 Panel & 5 Panel
		EFF. DATE: 21 / 04 /2021

Number of Pages: 88

Technical Committee



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: SCM-SPEC/XM/3&5 Panel

Rev.#: 0

Effective Date-21/04/2021

#### (i) Document Approval & Control Status

	Compiled by	Verified by	Approved by
Name	Sri.Harilal.V	Smt.Geetha.M	Mr. Sanal Kumar.K
Position	Assistant Executive Engineer (Supply Chain Management)	Executive Engineer (Supply Chain Management)	Chief Engineer (Supply Chain Management)
Date	20/04/2021	21/04/2021	21/04/2021
Signature	Sd/	Sd/	Sd/

#### (ii) Amendments and History

Sec. #	Rev. #	Date	History of Change



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

#### 1. PURPOSE:

Purpose of this document is to document updates & history, upkeep and publish the specifications related to **33kV Indoor VCB 3 panel sets and 5 panel sets** in a professional manner.

#### 2. SCOPE:

The Scope of this document is to inform and alert all relevant stakeholders including KSEBL, Public, KSERC etc regarding the current specifications and historical changes adopted in specifications of **33kV Indoor VCB 3 panel sets and 5 panel sets** used in field by KSEBL

#### 3. RESPONSIBILITY:

**The Executive Engineer (M), Office of Chief Engineer, Supply Chain Management** shall compile and take necessary steps to publish the specification in KSEBL website and shall inform relevant stakeholders regarding updates and revisions

#### 4. PROCEDURE FOR REVISION:

Modifications if any, in the technical specification will be incorporated as **Revisions**. Any changes in values, minor corrections in pages, incorporation of small details etc. will be considered as Minor Modification. **The Revisions due to minor modifications will be assigned as Rev. No.0.1, 0.2 etc.**

A complete updation of the technical specification will be considered as Major modification. **The Revisions due to major modifications will be assigned as Rev. No.1.0, 2.0 etc.**

All the details of regarding the revisions (both minor and major) will be incorporated in **“(ii)-Amendments and history”** above.

The concerned officers, in consultation with the Technical Committee will review and suggest changes required and the revision suggestion will be approved by **Chief Engineer (SCM)**. Those who notice any discrepancy or have any suggestion regarding revision, may bring the matter to the attention of Chief Engineer (SCM) in writing or through e-mail id:**cescm@kseb.in**



# SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

## TECHNICAL SPECIFICATION

### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: SCM-SPEC/XM/3&5 Panel

Rev.#: 0

Effective Date-21/04/2021

## CONTENTS

1. SCOPE OF SUPPLY .....	6
2. STANDARDS .....	6
3. CLIMATIC CONDITIONS .....	7
4. SYSTEM DATA .....	8
5. EQUIPMENT TYPE .....	8
6. RATING .....	8
7. CONSTRUCTIONAL FEATURES.....	12
8. PAINTING .....	14
9. NAME PLATE AND IDENTIFICATION MARKINGS .....	14
10. LABELLING .....	15
11. BUS BARS AND THE BUS CHAMBER .....	15
12. CIRCUIT BREAKERS .....	16
13. HV CABLE CONNECTION .....	16
14. CIRCUIT BREAKER OPERATING MECHANISM .....	16
15. GUARDING SHUTTERS .....	17
16. INTERLOCKING GEAR .....	17
17. EARTHING .....	20
18. PANEL WIRING .....	21
19. TERMINAL BLOCKS .....	22
20. INDICATING INSTRUMENTS.....	22
21. TEST TERMINAL BLOCK .....	23
22. INDICATING LAMPS .....	24
23. PUSH BUTTONS .....	24
24. SELECTOR SWITCH .....	25



# SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

## TECHNICAL SPECIFICATION

### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: SCM-SPEC/XM/3&5 Panel

Rev.#: 0

Effective Date-21/04/2021

25. RELAYS .....	25
26. RELAY FEATURES .....	27
27. ANNUNCIATOR .....	29
28. SPACE HEATERS .....	32
29. INTERIOR LIGHTING AND RECEPTACLES .....	32
30. MCBS, SWITCHES, FUSES AND LINKS .....	33
31. TESTS .....	33
32. DRAWINGS/ DOCUMENTATION .....	34
33. SOFTWARE FOR IEDS/ NUMERICAL RELAYS/ METERS .....	36
34. PACKING AND FORWARDING .....	37
35. SCHEDULE OF EQUIPMENTS FOR 5 PANEL SETS .....	37
36. LIST OF SPARES TO BE PROVIDED .....	48
37. GUARANTEED TECHNICAL PARTICULARS (5 PANEL SETS & 3 PANEL SETS) .....	50



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: SCM-SPEC/XM/3&5 Panel

Rev.#: 0

Effective Date-21/04/2021

### TECHNICAL SPECIFICATIONS FOR 33 kV INDOOR SWITCHGEAR 5 PANEL SET & 3 PANEL SET

#### 1.0) SCOPE OF SUPPLY:-

This covers the design, documentation, engineering, manufacture, inspection, testing at suppliers works packing and delivery at site, support for commissioning and after sales support of

- Extensible type 5 panel 33 kV switchboard consisting of 2 Nos of Incomer panels (Secondary side of 110/33 kV Transformers). 1 No of Bus Coupler and 2 Nos of outgoing Feeder Panels.
- 33 kV Indoor VCB 3 Panel Set consisting of 1 no. feeder panel (Incomer) and 2 nos transformer panels (outgoing) with facilities for adding two more panels if required in future, with one additional panel at each end, along with spares to be installed at various sub stations of KSEBL.

The equipment to be supplied against this specification is required for vital installations where continuity of service is very important. The design, materials and manufacture of the equipment shall therefore, be of highest order to ensure continuous and trouble free service over the years.

The manufacturer has to design the schematic for protection and control of all equipments including monitoring indications, visual and audible alarm, interlocking schemes among different equipment.

Any other requirement which are not specifically covered here but which are necessary for successful commissioning and operation of the Sub station is also within the scope of the contract.

#### 2.0) STANDARDS:-

Material, equipment and methods used in the manufacture of switchboard shall conform to the latest edition of following.

Standard Name / No.	Standard's Description
IEC: 62271-1, EC: 62271-3, IEC: 60298, IEC: 62271-200, IEC: 60529. IS: 3427, IS 12729, IS 12063, IS:13947, IS: 9046, IS: 3427/69	Switchgear and control gear
IEC 62271-100, IS 13118	Circuit Breaker
IEC 60947	Low Voltage Switchgear and Control gear
IS: 13010, IS: 722/64, BS: 37	Energy Meters
IS/IEC 60529	Degrees of protection provided for enclosures
IS :6005	Code of practice for phosphating iron and steel
IS :5	Colours for ready mixed paints and enamels
IS: 694	PVC insulated cables up to and including 1100V
IS:5578/1984	Guide for uniform system of marking and identification



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

	of conductors and apparatus terminals.
IS:11954	Guide for colour coding of Electrical Mimic Diagram
IS:1248 & IS:2419	Indicating Instruments
IS13947 (Part 5/ Sec 1) 2004,	Control Switches
IS13947 (Part 5/ Sec 1) 2004	Push Buttons
IS 14697	HT Static Tri vector TOD Energy Meter
IS:9224(part II)	HRC Cartridge fuse links
IS:3842	Application guide for protection
IS:3231, IEC 61000, IEC 60068, IEC 60529, IEC 61010-1	Electrical relays for power system protection
IS:8686	Static Protective Relays
IEC 60255	Numerical Relays
IEC 61850	Communication Networks and Systems in Sub Station
IEC 6100-4-29	DC Voltage dips and interruptions/ variations
IS 2705,IEC:60185	Current Transformer
IS 3156 , IEC:60186	Voltage Transformer
IS 3072	Code of practice for installation and maintenance of switchgear
IS 375, BS: 159/67	Arrangement of switchgear bus bars, main connection and auxiliary wiring
IS 9385	HV Fuses

Equipment complying with other internationally recognized standards will also be considered if it ensures performance equivalent or superior to above mentioned standards.

- 2.1. In the event of supply of equipment conforming to any international/internationally recognized standards other than standards listed above, the salient features of comparison shall be brought out and furnished along with the bid. One copy of such standard specification in English language shall be enclosed with the tender without any additional cost.
- 2.2. The equipment provided shall also comply with latest revisions of Indian Electricity Act , CEA Guidelines and any other applicable statutory provisions, rules and regulations.

#### 3.0) **CLIMATIC CONDITIONS:-**

- 3.1) The climatic conditions at site under which the equipment shall operate satisfactorily are as follows.

Maximum ambient air temperature	50 <sup>o</sup> C
Maximum ambient air temperature in shade	40 <sup>o</sup> C
Minimum ambient temperature in shade	17 <sup>o</sup> C
Maximum Relative humidity	100.00%
Average annual rainfall	3000mm
Average number of rainy days per annum	130
Maximum wind pressure	100Kg/sq.m
Climatic Condition:	Moderately hot and humid tropical climate conducive to rust and fungus growth

- 3.2) The climatic conditions are prone to wide variations in ambient conditions and hence the equipment shall be of suitable design to work satisfactorily under these conditions.

**3.3)** For the purpose of this specification, the reference ambient temperature would be 40 °C.

**4.0) SYSTEM DATA:-**

Frequency	:	50 Hz
Nominal System Voltage	:	33 kV
Highest System Voltage	:	36 kV
Rated short time current	:	31.5 kA for 3 seconds
Power frequency withstand voltage	:	70 kV
Basic insulation level	:	170 kV
System Neutral	:	Solidly earthed.
<b>Control Supply</b>	:	<b>110 V DC</b>

**5.0. EQUIPMENT TYPE:-** The switchgear shall be self standing air insulated and fully metal clad. The circuit breakers shall be of vacuum draw-out type, arranged for vertical or horizontal isolation of the drawn- out breaker. The switchgear shall be suitable for indoor installation. They shall be of robust construction and dust and vermin proof. Panel should be provided with 3 insulated bus bars and shall have facility for extension by adding individual cubicles at either end. **Circuit Breaker truck shall have 'Rack in/out' facility without opening of the doors.**

**The equipment shall comply Internal ARC Class IAC AFLR 25kA/1Sec and the Circuit Breaker shall be E2 M2 C2 Class as per IEC 62271-200.;**

**6.0. RATING:-** The complete switchgear equipments shall be designed for operation at normal system voltage of 33000 volts between phases and shall be capable of carrying a short time current equivalent to the symmetrical short circuit breaking capacity of not less than 1500 MVA. The ratings of circuit breakers, current transformers, potential transformers and bus bars are given below.

**a) CIRCUIT BREAKERS:-**

Sl.No.	Description	3 Panel Sets	5 Panel Sets
1)	Number of poles	3	3
2)	Frequency	50 Hz	50 Hz
3)	Nominal System Voltage	33kV	33kV
4)	Highest System Voltage	36kV	36kV
5)	Rated current	1250A	1250A
6)	Interrupting capacity	1500MVA	1500MVA
7)	Rated short time current	25kA for 3 Seconds	31.5kA for 3 Seconds
8)	Power frequency withstand voltage	70kV	70kV
9)	Basic insulation level	170kV	170kV

**b) CURRENT TRANSFORMERS:-**

i) For **5 Panel Sets** the current transformers shall have sufficient rating and shall be suitable for the instruments, protection relays etc. used in the





## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

equipment. Separate current transformers shall be used for metering and protection or alternatively CTs with multiple secondary cores may be used. Resin cast CTs with class E insulation or better shall be preferred. Outgoing UG cable feeder panel to be provided with 3 Nos. of CTs each having 2 secondary cores, one for metering and the other for O/C and E/F protection. In the case of Incomer panel (Secondary side of 110/ 33kV Transformer), 3 Nos. of CTs each having 4 secondary cores, one for metering, one for O/C and E/F protection, one for Differential protection plus REF protection and one for bus bar protection. In Bus Coupler Panel 3 Nos. of CTs having 1 core for Bus bar protection shall be provided for either side of the bus coupler breaker. The CT secondary terminals shall be easily accessible for testing by removing the back door. One number outdoor type neutral current transformer with CT ratio 600-300/1, PS Class for REF protection (Secondary side of 110/33 kV Transformer) to be supplied with the Incomer panel. Cables from Neutral CT for REF protection, Cables for Differential protection, inter trip connections, DC, AC inputs etc shall be brought to a terminal box on the back side of Incomer panels (Secondary side of 110/33 kV Transformer) with 20 Nos spare terminals.

The VA rating, accuracy limit factors etc. of the CT shall be suitable for the instruments, relays and other equipment used in the panel.

<b>Current Transformers</b>					
<b>Transformation Ratio</b>					
a)	Incomer panels (Secondary side of 110/33 kV Transformer)	-	600/300/5-5-1-1A		
b)	Feeder Panels (Outgoing)	-	300/5-5 A		
<b>Rating</b>					
		Core -1	Core -2	Core -3	Core -4
1)	Secondary Current	5 A	5 A	1 A	1 A
2)	Rated output	15 VA	15 VA	-	-
3)	Class of Accuracy	10 P	0.2 S	PS	PS
4)	Accuracy limit factor	10	-	-	-
For transformer panels, Core 3 & Core 4 are for Differential plus REF protection and Bus bar protection.					
CT requirements shall be as under.					
Minimum Knee Point Voltage			650 V at Lower ratio		
Maximum excitation current at $V_k/2$			30 – 40 mA		
Class of Accuracy			PS		
Secondary Resistance at 75°C.			2.5 Ohms		
<b>NEUTRAL CTs</b>			<b>Outdoor type</b>		
Ratio			600/300- 1 A		
Class of Accuracy			PS		



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

Minimum Knee Point Voltage	650 V at Lower ratio
Maximum excitation current at $V_k/2$	30 – 40 mA
Secondary Resistance at 75°C.	2.5 Ohms

- ii) For **3 Panel Sets** the current transformers shall have sufficient rating and shall be suitable for the instruments, protection relays etc. used in the equipment. Separate current transformers shall be used for metering and protection or alternatively CTs with multiple secondary cores may be used. Resin cast CTs with class E insulation or better shall be preferred. Feeders may be provided with 3 Nos. of CTs each having 2 Nos. of secondary cores, one core for use with O/C and E/F relays and the other core for metering. In the case of transformer feeders, each CT shall have 3 secondary cores, one for metering, one for over current and E/F protection, third one for REF protection. **The CT secondary terminals shall be easily accessible for testing by removing the bolted back door.**

**One number outdoor type neutral current transformer with ratio 200-100/1A for REF protection, to be supplied with each of the transformer panels.** Cables from Neutral CT for REF protection, inter trip connections, DC, AC inputs etc shall be brought to a terminal box on the back side of transformer feeder panels with 20 Nos. spare terminals.

The VA rating, accuracy limit factors etc. of the CT shall be suitable for the instruments, relays and other equipment used in the panel.

Current Transformers				
Transformation Ratio				
a)	Transformer Panels (Outgoing)	-	200/100/5-5-1 A	
b)	Feeder Panels (Incomer)	-	400/200/5-5 A	
Rating				
		Core -1	Core -2	Core -3
1)	Secondary current	5A	5A	1A
2)	Rated output (max)*	15 VA	15 VA	-
3)	Class of Accuracy	5 P	0.2 S	PS
4)	Accuracy limit factor	10	-	-
* Burdern calculation to be provided as per the metering and relay requirement with during detailed engineering. Back up protection CT used shall have good knee point more or less equal to PS Class. Instead of 5P10 Class PS Class core may be used to meet above requirement.				
Core 3 is required for REF protection in transformer panels only.				
Minimum Knee Point Voltage		300 V at Lower ratio		
Maximum excitation current at $V_k/2$		30 – 40 mA		
Class of Accuracy		PS		
Secondary Resistance at 75°C.		Less than 2.5 Ohms		
NEUTRAL CTs		Outdoor type		
Ratio		200-100/ 1 A		



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: <b>SCM-SPEC/XM/3&amp;5 Panel</b>	Rev.#: 0		Effective Date- <b>21/04/2021</b>
--	----------	--	-----------------------------------

Class of Accuracy	PS
Minimum Knee Point Voltage	300 V at Lower ratio
Maximum excitation current at $V_k/2$	30 – 40 mA
Secondary Resistance at 75°C.	Less than 2.5 Ohms

**c) POTENTIAL TRANSFORMERS:-** Potential Transformer as per the specifications shall be provided on the cable side on each incomer with fuse protection on both sides. The PT primary and secondary neutrals are to be earthed separately and brought out for testing purpose. The primary neutral earth shall get firm earth connection before phase connections are made, when pushed in to service. The PT may be of resin cast type. The wiring shall be as per standard procedures with proper ferruling and coloured wires.

1)	Type	Shall be cast resin type with insulation class of E or better.
2)	Mounting	<p>a) It shall be mounted on a with drawable carriage. Mounting of PT on the breaker truck is not acceptable. In case it is mounted on the panel rear top, access to the PT and the reinforcement in the panel for allowing a person to stand should be provided.</p> <p>b) Draw out type Potential Transformer is specified for easy isolation during testing and maintenance. If the bidder can provide crank operated switch for isolating the PT primary side, then fixed type can be accepted.</p>
3)	Neutral	The HV neutral connection to earth shall be easily accessible for disconnection during HV test.
Earthing of the System		Solidly earthed
Number of Secondary windings		One
Ratio		33 kV/ $\sqrt{3}$ : 110/ $\sqrt{3}$ Volts
Rated burden (Max)*		45 VA
Class of Accuracy		0.2
Purpose		Metering

All the current and potential transformers shall be mounted in such a manner that their secondary terminal connections are accessible for testing and maintenance purposes. The heavy duty terminal strips for CTs shall be provided with isolating links for testing without disconnecting cables.

\*Burden calculation to be provided as per the metering and relay requirement with during detailed engineering.

**d) BUS BARS:-** Bus bars shall be of constant cross sectional area throughout their length with connection as short and straight as possible. Bus bars shall be contained in a separate compartment with the general casing of the switchgear. Bus Bar shall be sleeved for full voltage. Sleeve shall be heat shrinkable. **PVC Sleeve in Bus Bar is not acceptable.** Suitable pressure relief facilities shall be provided and shall be extensible at both ends. Access to bus bar and the connections directly connected



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

there shall be achieved by the removal of the bolted covers. Such covers shall be clearly marked "**33kV LIVE**".

Sl.No.	Description	3 Panel Sets	5 Panel Sets
1)	Current rating	<b>1250 A</b> for a maximum temperature rise of 35°C	<b>2000 A</b> for a maximum temperature rise of 35°C
2)	Short time Current rating	25 kA for 3 seconds	31.5 kA for 3 seconds
3)	Bus bar size (Main)	a) 2 runs of 60x10mm (minimum) Electrolytic grade copper Insulated with heat shrinkable HT sleeve or better for main bus. b) Tubular bus made of specified copper grade and equivalent cross section and higher surface area can be accepted, provided adequate hardware is used for the bus joints with current density <1.2A/sq.mm..	a) 3 runs of 60x10mm (minimum) Electrolytic grade copper Insulated with heat shrinkable HT sleeve or better for main bus. b) Tubular bus made of specified copper grade and equivalent cross section and higher surface area can be accepted, provided adequate hardware is used for the bus joints with current density <1.2A/sq.mm.
4)	Bus bar size (for dropper/other)	1) Two run 60x10mm (minimum) for Incoming Feeder. 2) Two run 60x10mm (minimum) for Outgoing Feeder. EC grade copper Insulated with, heat shrinkable HT sleeve or better shall be used.	1) Three run 60x10mm (minimum) for Incoming Feeder. 2) Two run 60x10mm (minimum) for Outgoing Feeder. EC grade copper Insulated with, heat shrinkable HT sleeve or better shall be used.

**Bus bars shall be suitably holed and tinned at cable connection points. For bus bar joints, dropper connections and CT connections, there shall be minimum four bolts per joint.**

7.0. **CONSTRUCTIONAL FEATURES:-** The panels shall be of folded construction duly reinforced and shall be **free standing** and structurally independent taking into account the weight of the mounted equipments. All the panels shall have machine punched holes in their sides for the purpose of bolting on to the adjoining panels to form continuous board. Necessary foundation bolts required for site erection shall also be supplied. The cut outs for bus ducts shall be provided with blanking plates on the side of the end panels on both ends. All other holes provided at the end panels for facilitating extension shall be suitably blanked off. The design of panels shall be such that no permanent or harmful distortion occurs in them when being lifted by eye bolt or when moved into position by roller or transportation.



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

**It is responsibility of the supplier to ensure that the equipment specified and such unspecified complementary equipment required for completeness of the protections/control scheme shall be accommodated in the panels .**The panels shall be completely enclosed to ensure dust, moisture and vermin proof atmosphere. Design material selection and workman ship shall be such as to result in neat appearance, inside and outside with no welds, rivets etc.

Each stationary unit shall be provided with an instrument and relay panel of sheet steel construction, with hinged front door and a minimum of 2 Nos. locking handles. The instruments, meters and relays shall be of the flush mounting type and shall be mounted on the front of the panel.

1	Enclosure Type	Free standing, indoor, Fully compartmentalized, moisture, dust proof and Vermin-proof
2	Enclosure degree of protection	IP 4X for High Voltage compartment, IP 5X for low voltage compartment
3	Enclosure Material	CRCA steel
4	Load bearing members	Minimum 2.5 mm thick
5	Doors and covers	Minimum 2.0 mm thick
6	Gland Plate (detachable type)	3.0 mm MS detachable type or aluminum 5.0 mm for 3 core 400sq.mm XLPE cables
7	Extensibility	On either side
8	Separate compartment for	Bus bar, circuit breaker, HV incoming cable, HV outgoing cable, PT, LV instruments & relays.
9	Inspection window	For viewing indicators located in CB and to check switching device truck.( Transparent materials used shall be strong enough as per type tested design to withstand Internal Arc Test)
10	Breaker compartment door	Separate with lockable handle (design with breaker trolley as the front cover is not acceptable)
11	Breaker to bus bar compartment	Through seal off bushings
12	Breaker to cable compartment	Through seal off bushings
13	Pressure relief devices	To be provided for each HV Compartment
14	Bus support insulator	Non hygroscopic, track-resistant, high strength, epoxy insulators). Self supported Bus Bar can also be accepted
15	Fixing arrangement of doors	Concealed hinged Bolted with SS bolts Neoprene gaskets (Sufficient number of hinges are to be provided)
16	Required HV cable termination height in the cable compartment	Less than 1000mm for 33KV Cable.
17	Panel Base Frame	Steel base frame of standard sections.
18	Handle	Removable bolted covers for cable chamber and busbar chamber shall be provided with "C" type handles
19	Internal Arc Routing Baffles	To be provided for HV Compartments
20	Closed pressure relief duct	To be provided



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

21	Racking in/ Out of CB Truck with front door closed.	To be provided
22	Cable Earthing Truck	To be provided
23	Bus Earthing Truck	To be provided

#### 8.0) PAINTING:-

- Panel painting shall be done by the modern process of painting. All surface of the steel panel and frame work shall be sand blasted and suitably treated to remove rust, scale, foreign adhering matter or grease.
- A suitable rust resisting primer shall be applied on the interior and exterior surface of steel, which shall be followed by application of an undercoat suitable to serve as base and binder for the finishing coat.
- Details of Painting:-

Surface treatment	by seven (or eight) tank process
Phosphating	All sheet steel work shall be zinc phosphated in accordance with IS-6005 "Code of practice for phosphating iron and steel"
Paint type	Powder coated. Pure polyester base grade A finish.
External Paint shade and finish	Light grey shade 631 as per IS 5 with Structure Finish
Internal Paint shade and finish	White with semi glossy finish.
Base Frame Paint shade	Black
Paint thickness	Minimum 80 microns
Special Instruction	A small quantity of finishing paint shall be supplied for minor touching up required at site after installation of the panels.

Each coat of primer and finishing paint shall be of a slightly different shade to enable inspection of the painting.

#### 9.0. NAME PLATE AND IDENTIFICATION MARKINGS:-

- All instruments, relays and such other similar electrical devices mounted on the panel shall be provided with individual name plates with equipment designation bearing the manufacturer's name, serial identifying number and the Electrical rating data engraved.
- Similar identification plates shall be fixed on the exterior of the panel in appropriate places to indicate function of control switches, push button, control switch, DC fail test, accept reset etc. Suitable identification marks shall be provided for individual casing part of the relays and other equipment. Plates should be screwed and riveted to the Panel.



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: <b>SCM-SPEC/XM/3&amp;5 Panel</b>	Rev.#: 0		Effective Date- <b>21/04/2021</b>
--	----------	--	-----------------------------------

- c) Also on the top of each panel on front as well as rear side large and bold nameplates shall be provided for circuits/ feeders designations. 50mm wide black anodized aluminium plate bearing suitable circuit description etched in 30 mm size letters shall be provided for each panel and mounted on the top of the front and back side of panels. These plates shall be removable type.
- d) Each unit of panel shall be provided with a Name Plate located at the bottom on the front door and shall contain the following details :
  - i) Manufacturer's name
  - ii) P.O.no. and date
  - iii) Serial No./ Month & Year of Manufacture
  - iv) Drawing ref. no. pertaining to the panel.
  - v) Guarantee Period:
- e) Nameplates shall be made of non-rusting metal. Nameplates shall be black with **engraved/punched** lettering. The nameplates inscription and size of nameplate and letters shall be submitted to the purchaser for approval.
- f) Each Indicating instrument and meter shall be prominently marked with the quantity measured (ie. kV, A, MW).

1	Lettering	Engraved, with white letters on black background
2	Name plate for feeder description & number	On front and rear side of each panel giving feeder description. On the rear side the name plate shall be fixed on the frame.
3	Identification plates/labels at each cubicle and each instrument	Approved design (not stickers)
4	Manufacturer name plate	On Bottom of Front Door
5	Danger Board	Cable entry Box and wherever is required

**Each CB truck shall be provided with a name plate/ rating plate indicating the Make, Type, Sl.No., P.O. No., date of manufacture, rating as per standards like Voltage, Ampere, Breaking Capacity, STC, Internal Arc Class designation, Operating Sequence, Contact rating, etc. The Name/ Rating plate shall be got approved by KSEBL during detailed engineering.**

#### **10.0. LABELLING:-**

- a) All front mounted as well as internally mounted items including MCBs shall be provided with individual identification labels. Labels shall be mounted directly below the respective equipment and shall clearly indicate the equipment designation. Labelling shall be on aluminium anodised plates ( 50mmX15mm) of 1 mm thickness, letters are to be properly engraved. Letter size 75mm.



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

- b) All front mounted equipment shall also be provided at the rear with individual name identification labels engraved with the tag numbers corresponding to the one shown in the panel internal wiring to facilitate easy tracing of the wiring. The nameplates shall be mounted directly below the respective equipment and shall not be hidden by the equipment wiring.

- 11.0. BUS BARS AND THE BUS CHAMBER:-** The bus bars and connectors between the various pieces of apparatus forming the equipment shall be of electrolytic copper and suitably insulated with **HT heat shrinkable sleeves** and shall withstand the mechanical and electrical stresses due to short circuit. The bus bar supports and other insulating barriers shall be of materials, suitable for service under tropical climatic conditions. **PVC Sleeves are not acceptable.**

The bus bars shall be so arranged that they can be extended in length without difficulty. Interconnecting Bus Bar Links are to be provided. Provision shall be made for expansion and contraction of bus bars and connectors with variation of temperature. The bus bar chamber shall be air insulated.

- 12.0. **CIRCUIT BREAKERS:-** The circuit breaker shall be of vacuum type and shall have a minimum three phase short circuit rupturing rating of 1500 MVA. Doors shall be provided for all circuit breakers. Visual indication of spring/discharged condition shall be provided.

**Vacuum interrupters of the circuit breakers shall be completely encapsulated in epoxy housing. The Circuit Breaker shall be suitable for E2 M2 & C2 class duty.** The offered circuit breaker should have valid type tests to support the afore-mentioned duty class.

Means shall be provided for isolating circuit breaker unit. There shall be easy access to contacts for inspection and repairs. The breaker shall be mounted on horizontal withdrawable truck with horizontal or vertical isolators. **Circuit Breaker truck shall have 'Rack in/out' facility without opening of the doors. There shall be three positions viz; "Service", "Test" and "Isolated".** In Service position the Main & Auxiliary control contacts shall remain connected. In Test Position the Main contact shall remain disconnected, Shutters closed, Auxiliary Control contacts shall remain connected and the Circuit Breaker shall remain in the apparatus enclosure with the compartment door closed. **Locking of Circuit Breaker shall be possible in Service and Test Position.** A position indicator (both mechanical (on the CB) and Electrical (through LED lamps in the LT compartment door) shall be provided for indicating the Service, Test position, etc. Provision for remote indication of Service, Test and Isolated position of Circuit Breaker shall be provided by wiring the spare contacts to terminal block.

Suitable guiding arrangements shall be provided for the racking handle of Circuit Breaker truck, to ensure easy alignment of entry hole in door with slot/socket in Circuit Breaker truck. Racking handle entry hole shall be positioned such that sufficient clearance from floor level is available during operation.

- 13.0. **HV CABLE CONNECTION:** The power cable entry/exit point shall be provided with a removable gland plate and is located at the base of the cable compartments.





## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

- a) For 3 panel sets suitable provision shall be made on removable gland plates for 3 core 33kV 300 sq.mm, Aluminium XLPE Cables. Brass Glands suitable for above shall be provided.
- b) For 5 panel sets suitable provision shall be made on removable gland plates for 3 core 33kV 400 sq.mm, Aluminium XLPE Cables. Brass Glands suitable for above shall be provided.

14.0. **CIRCUIT BREAKER OPERATING MECHANISM:-** The circuit breaker shall be arranged for hand charged spring stored energy operation type. Motor operating mechanism shall be provided in addition. The motor shall be suitable for **230V AC** operation. The tripping mechanism shall have both mechanical and electrical releases. Mechanical release operated by means of push buttons and electrical releases by means of protective relays. The operating mechanism shall be trip free as defined in clause 2-38 of IS.2516 Part -I 1963. The trip coil and closing shall be suitable for connection to a 110 Volt DC supply. Hand trip device shall also be provided. The tripping circuit shall allow operation with 70 to 110% of rated DC auxiliary voltage and closing circuit shall allow 85 to 110% of rated DC auxiliary voltage. The spring charging motor shall operate from 90% to 110% of rated voltage. Provision for switching off the breaker mechanically shall be available in the front side of the panel without opening the door. There shall be three positions namely Service, Test, Isolated.

The circuit breaker operating mechanism shall be provided with a mechanical status indicating device to show whether the breaker is **Open or Close**. This indication shall be visible through the front glass window of the CB.

Continuous glowing lamp indication (LED) shall be provided for indicating Trip healthy, DC healthy and Breaker ON/OFF with appropriate labels. Separate electro-mechanical relay shall be provided for continuous trip circuit monitoring. Trip healthy indication (pre-close & post close) shall cover all contacts in between the trip coil and the relay contacts.

Provision shall be made for temporarily completing the trip circuit connection to the circuit breaker when it is isolated in order to permit circuit breaker to be operating for testing purpose.

The insulators for the circuit breaker stationary contacts and supports shall be porcelain or any other approved material which is non-hygroscopic and unaffected by moisture. The circuit breaker shall be provided with necessary heavy duty auxiliary switches for indication, protection, control and other services required. The connections of the control wiring from the stationery portion of the switchgear to its movable portion shall be arranged through secondary contacts of robust design.

15.0. **GUARDING SHUTTERS:-** The stationary isolating contacts connected to the bus bars, the voltage transformers and the incoming and outgoing cables of the switchgear shall be provided with cover (painted & marked "33 KV LIVE ") to prevent access when the circuit breaker or voltage transformer is withdrawn. The covers shall be opened or closed automatically by the positive movement of the circuit breaker or the voltage transformer.

16.0. **INTERLOCKING GEAR:-** The switchgear shall be provided with efficient interlocking gear to prevent.

- 1) The breaker being removed while in service.
- 2) The breaker being inserted in the 'ON' Position. It should not be possible to Rack-in the Circuit Breaker from the Test to the Service Position unless and until the Circuit Breaker is in Switched Off condition, Circuit Breaker Chamber Door closed and Control plug is connected.
- 3) Breaker withdrawal before switching off the vacuum bottle and unlocking the interlocking lever.
- 4) The closing of the circuit breaker when its terminals are not properly engaged with the stationary contacts.
- 5) Access to live parts of the switchgear when the circuit breaker is withdrawn.
- 6) The circuit breaker being put in service without its control / auxiliary wiring and without LV control plug connected.
- 7) Removal of Control wiring / plug shall not be possible when the circuit breaker is in Service Position.

<b>A Circuit breaker</b>		
1	Mounting	On with-drawable truck or carriage, with locking facility in service position and test position.
2	Interrupting medium	Vacuum
3	Breaker operation	Three separate identical single pole units operated through the common shaft.
4	Operating mechanism	Re-strike free, trip free, with electrical anti-pumping feature
		One O-C-O operation possible after failure of power supply to the spring charging motor.
		Motor wound, spring, charged, stored energy type with manual charging facility
5	ON/OFF/Emergency trip push button	i) Manual / mechanical ii) RED coloured Emergency Off push button will be provided with a Red colored protective flap. iii) Mechanical ON shall have padlocking facility.
6	Mechanical ON-OFF indication	On breaker trolley front and electrical indication (LED) on the LT panel door.
7	Operation counter	On breaker trolley front
8	Mechanism charge/discharge indicator	On breaker trolley front and "Spring Charged" electrical indication (LED) on the LT panel door.
9	Breaker positions	Service, test and isolated mechanical position indicator on the breaker trolley front and electrical indication (LED) on the LT panel door.

**TECHNICAL SPECIFICATION**

**33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS**

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

10	Inter changeability	Possible, only with breaker of same rating
11	Breaker control	On panel front only
12	Handle	Breaker shall be provided with handles for easy handling, rack in-out operation and manual spring charging as applicable.
13	Operating Sequence	O-0.3 sec-CO-3 min-CO
<b>B Functional Requirements</b>		
1	Interlock and safety devices	
2	Breaker compartment door opening	Can't be opened unless breaker is OFF in Service Position and irrespective of Breaker Status in Test and Isolated positions.
3	Breaker compartment door closing	Should be possible even when breaker in isolated position.
4	Racking mechanism safety interlock	Mechanical type
5	Racking in or out of breaker inhibited	When the breaker is closed
6	Racking in the circuit breaker to Service Position inhibited	Unless the control plug is fully engaged, Circuit Breaker Open and Compartment door closed
7	Disconnection of control plug inhibited	As long as the breaker is in service position
8	Locking of Circuit Breaker movement	In Service, Test and Isolated position
<b>C Additional Requirement</b>		
1	Exposure to live parts	In case the breaker panel door is required to be opened during a contingency, the personnel should not be exposed to any live parts. Suitable shrouds / barriers / insulating sleeves should be provided as required.
2	Breaker handling	In case the breaker is mounted on the carriage, which does not naturally roll out on the floor, a trolley for handling the breaker is to be provided. The trolley arrangement should ensure that the isolated breaker can be easily rolled on to the trolley with easiness and taken away. Two trolleys per switchboard for each breaker type shall be included in offer.
3	Operation of breaker	Electrical and Manual in either Service or Test position and Manual in Isolated Position
4	Closing from local	Only when local/remote selector switch is in local position



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

5	Closing from remote	Only when local/remote selector switch is in remote position
6	Manual Tripping from local	Only when local/remote selector switch is in local position except for emergency tripping
7	Protection Tripping	Irrespective of selector switch position
8	Testing of breaker	In test position keeping control plug connected
<b>D Safety shutters</b>		
1	Automatic safety shutter for fixed contacts	To fully cover contacts when breaker is withdrawn to test. Independent operating mechanism for bus bar & cable side shutters, separately pad lockable in closed position
2	Label for identification	For bus side and cable side shutters
3	Warning label on shutters of incoming and other connections	Clearly visible label "isolate elsewhere before opening shutter and earthing" be provided
<b>E Breaker electrical operation features</b>		
1	Trip circuit supervision	To be given for breaker close and open condition
2	Trip circuit supervision relay contact	For indication, alarm & to inhibit closing of breaker on failure of trip circuit healthiness.
3	Emergency Trip Push button contact	Wired to inhibit closing of breaker
4	Master trip relay contact	Wired to inhibit closing of breaker
5	DC Control supply bus in all panels	Fed by DC Incoming source
6	PT supply bus in all panels	Fed normally from respective incomer PT. In the event of multiple incomers, a PT selection scheme shall be provided to ensure supply to the meters in the corresponding panels in a section in the event of outage of the Incomer in that section. For switchboards with only one Incomer but with provision for additional feeders, necessary provision shall be made in the control wiring schematic for incorporating the PT selection scheme at a later stage on addition of the proposed future Incomer.
7	Trip circuit faulty	Wired to inhibit closing of breaker

17.0. **EARTHING:-** Provision shall be arranged to extend the earth connection to V C B truck by means of a pair of fixed and moving contacts automatically engaging when power contacts are engaged.

All panels shall be equipped with an earth fixed along the inside base of panels. The materials and the sizes of the bus bar shall be at least 50x6 mm electrolytic grade tinned copper flat unless specified otherwise. When several panels are mounted adjoining each



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

other, the earth bus shall be continuous and necessary connectors and clamps for this purpose shall be included in the scope of supply. Provision shall be made for extending the earth bus bar to future adjoining panels on either side. Provision shall be made on the earth bus bar of the end panels for connecting to purchaser's earthing grid. Necessary terminal clamps and connectors for this purpose shall be included in the scope of supply. All metallic case of relays, instruments and other panel mounted equipments shall be connected to earth bus by independent copper wire of size not less than **6 sq.mm**. The colour of earthing wire shall be green. Earthing wire shall be connected on terminals with suitable clamp connections and soldering shall not be permitted. VT and CT neutral or common lead shall be earthed at one place at the terminal blocks where they enter the panel. Such earthing shall be made through links so that earthing may be removed from one group without disturbing continuity of earthing system for other groups.

Equipment Earthing		
1	Material of earthing bus	Electrolytic Grade Tinned Copper
2	Earth bus joints	All bolted joints in the bus will be effected by connection of two bolts.
3	Rating	Sized for rated short circuit current for 3s seconds.
4	Enclosure and non-current carrying part of the switchboard/ components	Effectively bonded to the earth bus
5	Hinged doors	Earthed through flexible copper braid
6	Circuit breaker frame /	Earthed before the main circuit breaker contacts/control

**18.0. PANEL WIRING:-** All panel instrument wiring shall be neatly fixed in single layer, on the sides of the cubicles and shall be carried out with tinned copper wire, PVC insulated and of cross section of not less than 1.5 sq.mm. The CT and PT wires shall have a minimum cross section of 4sq.mm and properly coloured (red, yellow, blue & black) wires shall be used for each phase. The small wiring shall be terminated in suitable terminal strips easily accessible for maintenance purposes. Round ring type ferrules are to be used in all cases. 'U' type or pin type shall not be used.

All wires on the panels and multicore cables shall have PVC ferrules of the interlocking type. The ferrules shall be white or yellow in colour but all tripping circuits shall be provided with red ferrules marked 'Trip'. The marking on the ferrules shall be black in colour. The characters on the interlocking type ferrules shall be deeply engraved ensuring maximum permanency.

The panel wiring shall be **1100V** grade with copper conductor and shall conform to ISS.694. Both ends of wire are to be provided with colour bands with the same number as shown to facilitate easy maintenance and inspection.

Internal Wiring		
1	Internal wiring	1100V grade PVC insulated stranded flexible copper

**TECHNICAL SPECIFICATION**

**33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS**

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

		wire. ( <b>FRLS</b> )
2	Size	4 sq. mm for CT circuit, 4 sq mm for PT and 1.5 sq. mm for control circuit, 6 sq mm for earthing (minimum)
3	Colour code	
4	PT	R ph – Red Y Ph – Yellow B Ph – Blue Neutral – Black
5	CT	R ph – Red Y Ph – Yellow B Ph – Blue Neutral – Black
6	Others	DC – grey, AC-black, Earth – green
7	Ferrules	At both ends of wire
8	Ferrule type	Interlocked type (one additional red colour ferrule for all wires in trip circuit)
9	Lugs	Tinned copper, pre-insulated, round type.
10	Spare contacts of relays, timers etc	Wired up to the terminal blocks
11	Wiring enclosure	Plastic channels, inter panel wiring through PVC sleeves or suitable grommets.
12	Inter panel wiring	Wiring with ferrule to be terminated in the adjacent shipping section will be supplied with one end terminated and the other end bunched and coiled.

19.0. **TERMINAL BLOCKS:-** Terminal blocks shall be 1100V grade and have 10 amps continuous rating, one piece moulded, complete with insulated barriers, stud type terminal, washers, nuts, lock nuts and identification strips. Terminal block design shall include white fibre marking strip with clear plastic, slip-on/clip-on terminal covers.

Marking on the terminal strips shall correspond to wire number in the wiring diagrams. Not more than 2 wires shall be connected to any terminal. Suitable supports shall be provided for the incoming cables. The terminal blocks shall be arranged to provide maximum accessibility to all conductor terminations. The terminal blocks shall be fully enclosed with easily removable covers and made of moulded non-inflammable plastic material with bases and barriers moulded integrally.

Terminal blocks for current transformer and voltage transformer secondary leads shall be provided with test links and isolating facilities. Also current transformer secondary leads shall be provided with short circuiting and earthing facilities.

At least 20% spare terminals for all circuits shall be provided on each panel and these spare terminals shall be uniformly distributed on all terminal blocks.

1	Terminal Blocks (TB)	1100V grade, 10 amps min. rating,
2	Terminal for CT secondary leads	With provision for shorting with screw driver operated sliding link.
3	Spare terminals	20% in each TB row
4	TB shrouds & separators	Moulded non-inflammable plastic material
5	Clearance	
6	Clearance between 2 sets of TB	100 mm min.
7	Clearance with cable gland plate	250 mm min



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

8	Clearance between AC / DC set of TB	100 mm min
9	Test Terminal blocks	Screw driver operated stud type

20.0. **INDICATING INSTRUMENTS:-** The following indicating meters shall be provided on the panels. All the meters shall be flush mounting type.

1.
  - a) For 5 Panel Sets, 3 moving coil ammeter with 96x96 mm square face and 240° Scale to read 0 to 300A, 0 to 600A on all panels.
  - b) For 3 Panel Sets, 3 moving coil ammeter with 96x96 mm square face and 240° Scale to read 0 to 100A, 0 to 200A and 0 to 400 A on all panels.
2. Digital voltmeters of size 48x96 mm square with 20mm super bright LED display to show R-Y, Y-B, B-R voltages in incomer.
3. One 3-phase, 4-wire TOD Energy meter (5A) for all panels.

Frequency	:	50 Hz +/- 5%
P.F.	:	0.5 PF Lag - Unity - 0.5 P.F Lead
Burden	:	0.2VA max. per Volts/Amp. Input 3VA max.
Display	:	kW, kWh, kVAh, kVArh, MD, I, V, pf & Hz shall be available by scrolling. There can be 1, 2, or 3 mode of display, which facilitate more parameters. More accurate reading of power etc up to 6 decimal place shall be provided in the mode 3. Retains the last ordered reading even under power failure. Default setting for any parameter say kWh shall be given. Shall display import & export. Shall have data retrieval & logging facility. <b>Necessary software for feeding settings, commissioning, testing, etc and required inter facing cables shall be supplied with each set of Panel.</b>
Accuracy class	:	0.2S
Data communication	:	RS 485 port with MODBUS RTU protocol shall be provided. Data communication port with DLMS protocol also shall be provided.

#### **Meters**

Meters	Flush Mounted
<b>Ammeter</b>	Taut band, moving iron type
Size	96 X 96 mm
Panels where to be provided	All the panels
Accuracy class	1.0
<b>Voltmeter</b>	Digital
Size	48 X 96 mm

**TECHNICAL SPECIFICATION**

**33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS**

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

Panels where to be provided	Incomer
Accuracy class	0.5
<b>Energy meter</b>	ToD type Bi-directional 3phase,4 wire, 33kV/110V
Panels where to be provided	All panels
Accuracy Class	0.2S
Multifunctional meter	Scrolling facility with LCD display for parameters like power factor, KW,KVA,Ampere, etc. Accuracy 0.2S with RS485 port, communication port for DLMS protocol.

21.0. **TEST TERMINAL BLOCK:-** Switch board type, back connected semi flush mounting type test blocks with contacts suitably rated shall be provided with links or other device to enable a series device into circuit without causing open circuit in the CT secondary or to enable short circuiting of the CT Secondary. Test block covers shall be removable from the panels and shall be provided with suitable sealing arrangement to prevent unauthorized access to the test studs. Use 3 phase 4 wire Link type TTB with back connection for Energy meter and shall be placed near to the meter. All terminals, shorting links and screws shall be of brass and nickel-plated to prevent corrosion. All meters (A, MW, MVAR) shall be connected after TTB for testing their accuracies along with Energy meter calibration.

22.0. **INDICATING LAMPS:-** Indicating lamps (with bunched LEDs) shall be of miniature switchboard type, **Metallic**, suitable for panel mounting with rear terminal connections. The lamps should be mounted in such a way that it can be replaced easily. Lamps shall be provided with series connected resistors preferably built on the lamp assembly to avoid short-circuiting of control supply in the event of short-circuiting of lamp. These lamps shall be of screwed on type, unbreakable and moulded from heat resisting material. They shall be translucent to diffuse light. Integral inscription plates engraved with their function shall be provided. Unless otherwise stated, the lamp covers shall be coloured as follows:

1	Mounting	Flush mounted
2	Type	Metallic
3	Lamps	High intensity, clustered LED type
4	Breaker ON	Red
5	Breaker Off	Green
6	Spring Charged	Blue
7	DC Control supply fail	Yellow
8	Auto trip	Amber
9	Service position	Blue
10	Test Position	White



**TECHNICAL SPECIFICATION**

**33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS**

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

11	Heater circuit healthy	Yellow
12	Trip circuit healthy	White
13	PT supply as applicable	R, Y, B
14	Capacitive Voltage indicator for monitoring whether the Cable is Live or Dead	By LED indication and through Capacitive type feedback.

**23.0. PUSH BUTTONS:-**

- a) Push buttons of suitable colours shall be housed in metallic case, momentary contact type, semi flush mounted with rear terminal connection.
- b) These shall be suitably shrouded to prevent inadvertent operation.
- c) Integral inscription plates engraved with their function shall be provided.
- d) All push buttons shall have two normally closed and two normally open contacts comprising rivets of pure silver.
- e) **The contacts shall be able to make and carry 5A and break 1A Inductive load at 250 V DC.**

1	Mounting, Type	Flush mounted, momentary contact type
2	Casing	Metallic
3	Emergency trip push button	Red color with stay put (shrouded)
4	Accept push buttons	Black color – trip alarm / DC fail alarm
5	Reset push buttons	Yellow color – trip alarm / DC fail alarm
6	Test push buttons	Blue color – for heater circuit healthy
7	Rating	5 A

**24.0. SELECTOR SWITCH:-**

- a) They shall be of rotary operated type preferably with silver to silver contacts adequate making, carrying and breaking current rating.
- b) They shall be provided with easily removable protective terminal covers and escutcheon plates clearly marked to show operating position and shall be suitable for flush mounting with only switch front plate and operating handle projecting out.
- c) The connection shall be from the back.
- d) The contact assembly at the switch shall be enclosed in dust proof removable covers.
- e) The control springs shall be strong and robust enough to prevent inadvertent operation due to light touch.

**TECHNICAL SPECIFICATION**

**33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS**

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

1	Selector switches and switches and push button	Flush mounted on LV compartment door, with shrouded terminals
2	TNC Switch with pistol grip	spring return to normal position
3	Rotary ON/Off switches	For heater & spring charging circuits
4	Rating	16 A

**25.0. RELAYS:- Approved make of Relays: ABB/Alstom/GE/Siemens Siprotec/ SEL/Schneider- Micom**

- 1) Relays shall conform to the requirements of IS 3231(Electrical Relays for power system protection) or IS 8686 or IEC 60255 or other applicable approved standards, as the case may be.
- 2) Relays should be suitable for flush mounting on the front with connections from the rear.
- 3) Relays shall be rectangular in shape and shall be dust tight.
- 4) The auxiliary relays and timers shall be modular type.
- 5) All AC relays shall be suitable for operation at 50 Hz. AC Voltage operated relays shall be suitable for 110V PT secondaries and current operated relays for 1A/5A CT secondaries. DC auxiliary relays and timers shall be designed for DC voltage specified and shall operate satisfactorily between 70% and 110% of rated voltage. Voltage operated relays shall have adequate thermal capacity for continuous operations.
- 6) The protective relays shall be suitable for efficient and reliable operation of the protection scheme described in the description in the specification.
- 7) Necessary auxiliary relays and timers required for interlocking schemes for multiplying of contacts, suiting contact duties of protective relays, and monitoring of control supplies and circuits lock out relays monitoring circuits etc. and also required for the complete protection schemes described in the specification shall be provided.
- 8) All protective relays shall be provided with at least two pairs of potential free isolated output contacts. Auxiliary relays and timers shall have pairs of contact as required to complete the scheme.
- 9) Contacts shall be silver faced with spring action. Relay cases shall have adequate number of terminals for making potential free external connections to the relay coils and contacts. Paralleling of contacts, if any shall be done at the terminals on the casing of the relay.
- 10) All protective relays, auxiliary relays and timers except the lockout relays and interlocking relays specified should be provided with self-reset type contacts. All protective relays, trip relays and timers shall be provided with external manual reset positive action operation indicators provided with inscription subject to purchaser's approval.

**TECHNICAL SPECIFICATION**

**33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS**

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

- 11) No control relay that trip the power circuit breaker when the relay is de-energised shall be employed in the circuits.
- 12) Provision for easy isolation of trip circuits of each relay for purpose of testing and maintenance shall be incorporated. Suitable device for indication of operation of each protection shall be provided along with resetting device on front of the panel.
- 13) Auxiliary seal-in-units provided on the protective relays shall preferably be of shunt reinforcement type. All necessary provision for easy testing of relays shall be provided. If series relays are used the following shall be strictly ensured.
  - a) The operating time of the series seal in unit shall be sufficiently shorter than that of the trip coil or trip relay in series with which it operates to ensure definite operation of the flag indicator of relay.
  - b) Seal in unit shall obtain adequate current for operation when one or more relays operate simultaneously.
  - c) Impedance of the seal unit shall be small enough to permit satisfactory operation of the trip coils or trip relays when the D.C. supply voltage is minimum.
- 14) The printed circuit cards shall be of fiberglass type and the contact shall be gold plated. All connections with the connector pegs shall be through wire wrapping. All solder joints on the printed circuits boards shall be encapsulated or covered with lacquer for protection from environment.
- 15) The components shall be loaded by less than half of their rated values. The resistors shall be of carbon composition or metal oxide type and capacitors shall be plastic film or tantalum type. Stringent measure including shielding of long internal wiring should be taken to make relays immune to voltage spikes. The relays must withstand 5KV; 1x150 micro second 0.5 joule source energy impulses test or 1.5 MHz damped oscillations with initial value (zero to peak) of 2.5KV decay to half the initial value of 6 micro seconds with internal sources impedance of 150 ohms as per IEC Standard.
- 16) All relays shall be designed for operating under an ambient temperature of 50<sup>0</sup> C and 100% relative humidity.
- 17) All devices required for correct operation of each relay shall be provided by the supplier without any extra cost.
- 18) All numerical relays shall be provided with 'Relay Failure Annunciation contact'.
- 19) At least one output relay from all numerical relays shall be configured for any trip and shall be wired up to TB for testing purpose exclusively.
- 20) The supplier shall ensure that the terminals of the contacts of the relays are readily brought out for connections as required in the final approved scheme. The type of the relay case size offered shall not create any restrictions in the availability of the contact terminals for wiring connections.
- 21) Provision of DC cell for the protective relays as reliable stand by power supplies will not be acceptable.
- 22) **The numerical shall be stable and suitably protected against transient/ induced over voltage.**



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

#### 26.0. RELAY FEATURES:-

##### 26.1. Directional 3 Over Current & Earth Fault Relay:-

Type	Numerical low burden having directional 3 Over current and 1 Earth fault relay with 3 voltage inputs, measurement functions, 6BI, 8BO,s elf supervision, IEC 61850 compliant, with Disturbance recorder and Event logger
Current Rating	5 Amp.
Curve	IDMT & DT
Indicators	LED with resetting facility. LEDs shall be provided for indicating faulted phase (R,Y,B) during Over current and Earth Fault (E/F) when corresponding protections are acted.(programmable)
Communication	(I) Front Communication Port USB/RJ45 for connecting Laptop  (II) Rear Ethernet Port with IEC 61850
Binary Inputs/ Output (Minimum)	6/8 nos.
LBB features shall be provided and wired for relay in transformer panel so that in the event of Circuit Breaker failure in Transformer Panel incomer Breaker shall be tripped.	
<b>Setting Range</b>	
TMS for IDMT O/C and E/F	0.05 to 1.5 in steps of 0.01
IDMT O/C Protection current setting	50% to 250% in steps of 5%
IDMT E/F Protection current setting	5% to 100% in steps of 0.5%
High Set (50 & 50N) current setting	50% to 2500% in steps of 10%
LBB	With current supervision and re-trip

##### 26.2. REF relay and Busbar protection relay:-

Type	Numerical, High Impedance Instantaneous REF relay with seal-in type operation indicator with provision for reset and with suitable external stabilizing resistance (Variable 0-1000 Ohm) & Metrosil as applicable. Relay shall be tuned to the system frequency of 50Hz. 2Nos. High Impedance relay (1A Nominal CT) shall be provided for Bus bar protection one for each side. Out put of each shall trip respective incomer, feeders and Bus Coupler Breakers
Current Rating	1 Amp.
Indicator	LED with resetting facility



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

Communication	Front Communication Port USB/RJ45 for connecting Laptop
Setting Range	0.1A to 0.4 A
Contacts	3 contacts for trip, alarm, inter trip respectively and shall have two tripping contacts and two alarm contacts minimum as spare
Wiring shall be done so that Disturbance Recorder in 3 Over Current & Earth fault Relay shall be triggered on operation of REF Relay.	

**26.3. TRIP CIRCUIT SUPERVISION RELAY:-** The trip circuit of CBs shall be supervised by separate electromechanical / Static / Numerical relays. This scheme shall continuously monitor the trip circuit before and after closing of the circuit breaker. This scheme shall detect.

- (1) Failure of trip supply
- (2) Open circuit of trip circuits wiring
- (3) Failure of mechanism to complete the tripping operation.

The relays shall have necessary contacts to be connected to either the alarm bell or to the annunciator available in the panel for visual and audible indication of the failure of trip circuit with sufficient spare contacts. One bunched type LED bulb indication shall be provided for "Trip Circuit Healthy" continuously. It shall not be possible to close during trip circuit faulty condition.

**26.4. DC SUPPLY SUPERVISION RELAY:-** DC supply supervision scheme shall be provided in each panel using Electro-mechanical / Static type DC under voltage relay. In the event of failure of DC supply to annunciator, a bell operated by AC supply shall be energized. The alarm should be acknowledged through the alarm acknowledge push button of the panel.

**26.5. High Speed Tripping Relay:-** Following shall be the main features of tripping relays :

- i) Be instantaneous (Operating time not to exceed 10 ms).
- ii) Reset within 20 ms
- iii) Shall be high impedance type
- iv) Be DC operated - 110 V DC
- v) Have adequate contacts to meet the requirement of scheme, and minimum 2 nos NO & NC contacts shall be provided as spare.
- vi) Be provided with flag indicator
- vii) All contacts shall be reset with a single reset.
- viii) All tripping relays shall be high speed high burden type.
- ix) Normally closed contacts in series with the relay operating coil, shall be delayed for a period which will allow series flag relays to operate satisfactorily. All other tripping contacts should be instantaneous. i.e no intentional time delay.
- x) Work satisfactorily for an operating voltage range from 70% to 120% of rated voltage of the auxiliary voltage.

xi) High speed tripping relays shall prevent closing of the associated circuit breakers until reset. All tripping relays shall have inbuilt hand resettable flag indication.

xii) Be immune to capacitance discharge currents, which can result at the inception of an earth fault on DC wiring and immune to subsequent leakage current.

26.6. **Auxiliary Relay for transformer functions:-** Electro-mechanical flag type relay

- i. 4 element-30ABCD transformer TRIP functions)
- ii. 4 element- 30EFGH transformer ALARM functions)

27.0. **ANNUNCIATOR:-**

**27.1. Annunciator System:-** Alarm annunciation system shall be provided for the Panels by means of visual and audible alarm in order to draw the attention of the operator to the abnormal operating conditions or the operations of some protective device. The annunciation shall be divided into the following two categories.

- i) Emergency annunciation.
- ii) Warning annunciation.
- iii) The annunciation equipment shall be suitable for operation on DC supply as specified in the specification.

27.1.1. **Emergency Annunciation:-** This annunciation is used to draw the attention of the operator when the circuit breaker is tripped automatically. The audible annunciation shall be provided by means of "Hooter." The visual annunciation shall be flickering of common facia window provided on the respective panel on which the control of the tripped breaker is located. The tripped breaker shall be identified by the flickering of the corresponding position indication lamp.

27.1.2. **Warning Annunciation:-** The annunciation is used to draw the attention of the operator to the occurrence of an abnormal operating condition and then the tripping of the circuit breaker. The audible annunciations shall be provided by means of a bell and visual annunciation by flickering of the respective facia window. Certain numbers of alarms under this category have to be time delayed with the time delay adjustable between 2 to 10 seconds. The supplier shall provide arrangements for this purpose.

The audible alarm shall continue until the sound signal cancel push button is pressed. The sound signal cancel push button shall be common for cancellation of audible alarm hooter and bell.

27.1.3. The visual annunciation shall be provided by annunciation facia mounted on the top row of the panel. Necessary switching relays for the same shall be mounted inside the panel. It shall be provided with sufficient number of suitably sized rectangular facia with the size of the lettering not less than 5mm. Alarm inscriptions shall be engraved on each window in not more than three lines and shall be visible only when the facia light is on. The cover plates of the facia window shall be capable of easy removal to facilitate replacement of LEDs. The transparency of covers and wattage of the LEDs provided in the facia window shall be adequate to ensure clear visibility of the inscription from the location of the

**TECHNICAL SPECIFICATION**

**33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS**

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

operator's table in the control room having high illumination intensity. Use bunch of LED connected lamp window.

27.1.4. The sequence of operation of the annunciator shall be as follows:

Sl.No.	Alarm Condition	Fault Contact	Visual Annunciation	Audible Annunciation
i)	Normal	Open	OFF	OFF
ii)	Abnormal	Close	Flashing	ON
iii)	Accept Push Button Pressed	Close	Steady ON	OFF
		Open	Steady ON	OFF
iv)	Reset Push Button Pressed	Close	ON	OFF
		Open	OFF	OFF
v)	Lamp test Push button is pressed	Open	Steady ON	OFF

27.2. ELECTRONIC ANNUNCIATOR annunciation system described above shall also meet the following requirements.

- a) Suitable Multi-way Microprocessor based electronic Annunciator for the visual and audible alarm on the panel using bright LEDs shall be provided to indicate trip/alarm functions operated.
- b) Each Electronic Annunciator shall have provision for connection with accept/reset/lamp test/mute Push buttons for proper functions.
- c) Electronic annunciator shall have provision for connection with Electronic Buzzer/Hooter for Trip & Electronic Bell for Non-Trip Audio Alarm of common annunciation scheme.
- d) Electronic Annunciation shall have provision for flashing illuminating display with inscription for operation of respective Protection Relay.
- e) The Micro-Processor based Electronic Annunciator should have separate coloured windows for Trip & Non-Trip Annunciation for easy detection.
- f) Annunciator fascia units shall have translucent plastic windows for each alarm point.
- g) Electronic Annunciator shall have first Fault Indication Facilities & System Watch Dog.
- h) Annunciator facia plate shall be engraved in black lettering with respective alarm inscription as specified. Alarm inscriptions shall be engraved on each window in not more than three lines and size of the lettering shall be about 5 mm. The inscriptions shall be visible only when the respective facia LED will glow.
- i) Annunciator facia units shall be suitable for flush mounting on panels. Replacement of individual facia inscription plate and LED shall be possible from front of the panel.
- j) Unless otherwise specified, one alarm bell meant for non-trip alarms and one hooter meant for trip alarms shall be provided in each panel (mounted inside).

**TECHNICAL SPECIFICATION**

**33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS**

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

- k) Each annunciator shall be provided with 'Accept', 'Reset' and 'Test' push buttons, in addition to external Push Button for the same.
- l) Special precaution shall be taken by the manufacturer to ensure that spurious alarm conditions do not appear due to influence of external magnetic fields on the annunciator wiring and switching disturbances from the neighboring circuits within the panels.
- m) In case 'RESET' push button is pressed before abnormality is cleared, the LEDs shall continue to glow steadily and shall go out only when normal condition is restored.
- n) Any new annunciation appearing after the operation of 'Accept' for previous annunciation, shall provide a fresh audible alarm with accompanied visual alarm, even if the process of "acknowledging" or "resetting" of previous alarm is going on or is yet to be carried out.
- o) Visual and audible annunciation for the failure of D.C supply to the annunciation system shall also be provided and this annunciation shall operate on a 230 Volts AC supply with separate fuses. A separate voltage check relay (adjustable setting) for the failure of supply shall be provided and if the failure of supply exists for more than 2 to 3 sec, a facia shall light up and the bell shall sound. A separate push button shall be provided for cancellation of this bell alone but the facia window shall remain steadily lighted till the supply to the annunciation system is restored.
- p) The sound of the audible alarm (bell) provided for this annunciation shall be different from the audible alarm for warning signals.
- q) The annunciation system shall be capable of catering for at least 20 simultaneous signals at a time.
- r) One self-resetting push button shall be provided each for testing emergency annunciation and warning annunciation systems and for testing, the annunciation supply failure monitoring circuit. One self-resetting push button shall also be provided on each panel for testing the facia window lamps. These testing circuits shall be so connected that while testing is being done it shall not prevent the registering of any new annunciation that may land during the test.
- s) Provision shall be made for switching off the entire annunciation system.
- t) The self returning push buttons for Accept, Sound cancel and lamp test shall be common for both emergency and warning annunciations.
- u) The annunciation shall be of repetitive type and shall be capable of registering the fleeting signals. Minimum duration of the fleeting signals registered by the system shall be 15 milli seconds.

**28.0) SPACE HEATERS:-**

- a) 240 V, 50 HZ Tubular Space Heaters suitable for connection to the Single Phase A.C. Supply complete with On-Off Switches located at convenient position shall be provided in Breaker and to be to be mounted on an i n s u l a t o r .
- b) These shall not be mounted close to the wiring or any panel mounted equipment.



- c) The Watt loss per Unit surface of heater shall be low enough to keep surface temperature well below sensible heat but should be capable to keep 10°C above average ambient temperature in the rainy season but temperature shall not under any circumstances damage the insulation of wiring of the panel / other mounted equipment.
- d) A thermostat control unit with variable temperature shall be installed to control the heater.
- e) The 240 V AC supply for the heater shall be controlled by a suitably rated single pole miniature circuit breaker compartment to be mounted on an insulator.
- f) **Wiring connected to space heaters in the cubicle shall have porcelain beaded insulation over a safe length from heater terminals.**

**29.0. INTERIOR LIGHTING AND RECEPTACLES:-**

- a) The LV Chamber shall be illuminated by 11W LED lamp with fixture including reflector, front cover, etc connected to 230 Volt Single Phase A.C.
- b) The illumination of the interior shall be free from shadows and shall be planned to avoid any strain or fatigue to the wireman likely to be caused due to sub-normal or non-uniform illumination.
- c) A toggle switch or door operated switch shall be provided for control of A.C. lighting in each panel.
- d) One combined 15 Amps. 3-Pin and 5 Amps. 2-Pin Power Socket outlet together with Plus Pins shall be provided at convenient points in LV Chamber I for A.C. Supply.

**30.0. MCBS, SWITCHES, FUSES AND LINKS:-**

- a) Each panel shall be provided with necessary arrangements for receiving distribution, isolating and tripping of D.C and A.C supplies for various control, signaling, lighting and space heater circuit in an easily accessible location.
- b) The incoming and sub-circuits shall be separately provided with MCBs with auxiliary contacts that are extended for trip indication in each panel.
- c) Selection of the main and sub-circuits ratings shall be such as to ensure selective clearance of sub-circuit faults.
- d) All MCBs, Fuses and Links shall be of superior quality , bear ISI mark and shall have imprint of rating, voltage and circuit designation.

**31.0. TESTS:-**

**31.1. Type Test:-**

- a) The Manufacturer should submit the Type test report including **IP test of Panels and functional test** for all the protective relays carried out within **7 years** from the due date of submission of tender from CPRI/ NABL accredited Laboratory (or accreditation based on ISO/IEC/Guide 25/17025 or EN 45001 by the national



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

- accreditation body of the country where the lab is located.) / PHELA/KERI/KEMA/CESI laboratory /Govt. Recognized test house or Laboratory on the **tendered Items** as per IS/IEC/Technical specification with the tender documents.
- b) Following type test reports are to be submitted for the offered equipments. The tests shall be carried out with the same make and type of Vacuum Interrupter bottle offered in the bid.
- 1) Lightning Impulse Voltage Withstand test
  - 2) HV dry 1minute Power frequency withstand test.
  - 3) Short time 25kA 3Sec. for 3 Panel & 31.5kA, 3Sec. for 5 panel and Peak with stand current test
  - 4) Short circuit Test duties on Circuit Breaker.
  - 5) Temperature Rise Test.
  - 6) Internal Arc Test IAC AFLR 25KA/1 sec for CB compartment, cable compartment and busbar compartment as per IEC 62271-200.
  - 7) Type Test to prove Endurance E2 M2 C2
  - 8) Degree of Protection.
- c) Type Test reports of PT, CT, Neutral CT and Relays shall also be submitted.

#### 31.2. INSPECTION AT FACTORY:-

- a) Acceptance test at manufacturer's works in presence of purchaser's representatives shall be carried out. The supplier shall give at least 20 days notice of the date when the tests are to be carried out. Purchasers shall give the right to select any quantity of the item wise offered lot for testing, offered for inspection and in the event of failure in test(s), the purchaser shall have the right to reject the offered equipments.
- b) All components, relays, meters & annunciators provided in the panels are to be accepted only after successful hundred percent performance testing at testing department, if found required, by KSEBL.
- c) The inspection may be carried out by the KSEBL at any stage of manufacturing. The successful Manufacturer shall grant free access to the KSEBL's representative/s at a reasonable notice when the work is in progress. Inspection and acceptance of any equipment under this specification by the KSEBL, shall not relieve the supplier of his obligation of furnishing equipment in accordance with the specification and shall not prevent subsequent rejection if the equipment is found to be defective.
- d) The manufacturer shall keep the KSEBL informed in advance, about the manufacturing programme so that arrangement can be made from stage inspection.

**TECHNICAL SPECIFICATION**

**33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS**

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

- e) The KSEBL reserves the right to insist for witnessing the acceptance/routine testing of the bought out items. The supplier shall keep the KSEBL informed, in advance, about such testing programme.
- f) **Test at Factory :- Test procedures shall be forwarded along with inspection call.** The following Tests shall be carried out 6 copies of Test certificates shall be submitted for approval.
  - i) The complete switchgear shall be subjected to routine tests as specified in the relevant standards mentioned in clause 2 of Annexure I, Part II
  - ii) The individual components Viz. Circuit Breakers, CTs, PTs, relays and instruments shall also be subjected to routine tests as specified in the relevant standards mentioned in clause 2 of Annexure I,Part II.
- g) **The Equipments shall only be dispatched after approval of the test certificates and issue of Material Despatch Cum Clearance (MDCC) from KSEBL**

**32. Drawings/Documentation:-**

**32.1.** In the event of an order materializing , within 2 weeks of the receipt of order, Triplicate copies of the following drawings and literature shall be submitted. The drawing shall include **Cover Page, General Arrangement, Schematic , Terminal Connections and Bill of Materials** which are serially numbered.

**32.2.1.** Cover Page: Shall include Name of Panel, Customer Name, P.O. Ref, Drawing Number, Revision History of each sheet,Total number of sheets, etc .

**32.2.2.** Second Page shall give table containing description of each sheet.

**32.2.3.** General Arrangement drawing shall include

- a) Technical details of panel construction, general description, terminal notations,etc.
- b) Principal dimension details of each unit cubicles, complete assembly of panel .
- c) Front and rear views of the Panel with instrument and device positions marked.
- d) Foundation drawings and floor plans of control and Relay panels. Location of foundation bolts, cable slots and weights shall also be given on these drawings.
- e) Pictorial views of the Control Switches Terminal Blocks, Indication Instruments, Test Blocks and exploded views of draw out type instructions and Fuse Blocks.
- f) Name Plate , Rating Plate details
- g) Legend sheet describing symbolic representation of components.

**32.2.4.** Schematic Diagram sheets shall include circuit diagrams including the following:

- a) Single line diagram showing power circuit, protection and metering for each panel.
- b) AC & DC Distibution circuits.

**TECHNICAL SPECIFICATION**

**33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS**

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

- c) Indication circuits
- d) Metering Circuits
- e) Complete schematic drawings for annunciation system.
- f) Protection circuits
- g) voltage selection schemes
- h) Tripping circuits
- i) Closing Circuits
- j) Supervision Circuits
- k) Contact development drawings of all switches, relays etc.
- l) Trip Matrics and Inter locking Schemes.
- m) Terminal Connection diagrams and wiring schedule.
- n) Complete AC and DC Schematic drawings of elements of control and relay boards. These show all A.C. power connection and secondary connection for relay, meters etc. with vector relationship.
- o) Cable inter-connection drawings indicating terminal block numbers, number of cores, instruments, panels at which cable is to be connected etc. The supplier may submit any other drawings considered necessary in addition to the drawings stated above.

**32.2.5.** Bill of Materials showing quantity and description (Make, Model No., specification, etc) of all components used in line with specification. List of spares supplied with each panel also to be included in a separate sheet included in drawing.

**32.2.6.** Relevant Illustrative, descriptive literature shall be furnished.

**32.3.** Normally shall be granted within 30 days from receipt of the complete drawings.

**32.4.** The manufacturing of the equipment shall be strictly in accordance with the Approved Drawings and no deviation will be permitted without the written approval of the purchasing authority. All manufacturing work which is not as per the approval shall be at the suppliers risk.

**32.5.** All drawings shall conform to International standards Organization (ISO) 'A' series of drawing sheet. All drawings shall be in indelible ink. All dimensions and data shall be in S.I.Units.

**32.6.** It is desired that the complete schematic drawing is provided on a permanently laminated/engraved plate of suitable thickness which has to be bolted/riveted at the four corners on the inside face of rear door. In addition, one more plate of similar type and dimension shall be provided on the outside of the rear door providing guidelines and instructions for operation. The guidelines and schematic to be provided on the plates shall be as per approved drawings.

**32.7.** Before dispatch of equipment to various consignees, the supplier shall furnish 6 sets of drawings, Bill of materials, wiring Schedule, technical literature and commissioning Manuals in suitable files (hard copy as well as soft copy)



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

- 1) 2 sets per Control & Protection Panels shall be sent to concerned substation.
- 2) 2 sets per Control & Protection Panels shall be sent to consignee before the dispatch of equipment.
- 3) 1set per Control & Protection Panels shall be sent to Purchase Authority.
- 4) 1 set shall be provided inside the panel.

**32.8.** Supplier shall also furnish **one complete set of soft copy of the relevant "AS BUILT" drawings in CD/USB drive.** These shall be furnished to CE (SCM), immediately after the final inspection of various equipments before dispatch.

**32.9.** Approval of drawings/work by purchaser shall not relieve the supplier of his responsibility and liability for ensuring correctness and correct interpretation of the drawings for meeting the requirements of the latest revision of application standards, rules and codes of practices. The equipment shall conform in all respects to high standards of engineering, design, workmanship and latest revision of relevant standards at the time of ordering and purchaser shall have the power to reject any work or materials which, in his judgement is not in full accordance therewith.

33) **SOFTWARE FOR IEDS/NUMERICAL RELAYS/METERS:-** Full version of relay communication software with all features including software for Disturbance Record Analyser, licensed to KSEB Ltd. for relay testing & commissioning shall be provided in CD/USB DRIVE which shall also be used for subsequent installation if needed. The software shall have graphic capabilities for display and suitable interface to generate user defined reports in addition to the standard report forms. The interfacing cables and/ or interfacing devices required for communicating with the relay may be supplied along with relay testing and communication software.

Licensed copy of communication software, front & rear interfacing cables and hardware shall be supplied to upload/ download the data to/from the relay and from/to the laptop. The software shall be suitable for operations like switching, setting changes, analysis of fault record and to retrieve oscillographic fault data from the relay, as applicable.

Any future up-gradation in software/ firmware shall be provided with free of cost.

**34. PACKING AND FORWARDING:-**

- 1) The equipments shall be packed in crates suitable for vertical/horizontal transport as the case may be, and suitable to withstand handling during transport and outdoor storage during transit. The supplier shall be responsible for any damage to the equipment during transit, loading and unloading due to improper and inadequate packing. The easily damageable material shall be carefully packed and marked with the appropriate caution symbol. Wherever necessary, proper arrangement for lifting, such as lifting hooks etc., shall be provided. Any material found short inside the packing cases shall be supplied by supplier without any extra cost.
- 2) Each consignment shall be accompanied with a detailed packing list containing the following information.
  - 1) Name of consignee

**TECHNICAL SPECIFICATION**

**33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS**

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

- 2) Details of consignment-P.O/Name of Item/SI.No.,etc
  - 3) Destination
  - 4) Total weight of consignment
  - 5) Sign showing upper/lower side of the crate
  - 6) Handling and packing instructions
  - 7) Bill of material indicating contents of each package
3. The supplier shall ensure that the packing list and bill of material are approved by the purchaser before dispatch.

**35. SCHEDULE OF EQUIPMENTS for 5 Panel Sets:-**

**(1) Each set of 33kV, 1500 MVA 5 Panel Switch Board with Vacuum Circuit Breakers consisting of following:**

**a) Main Bus Bar Rating : 2000 A, 33kV**

**b) Incomer Panels (Secondary side of 110/33 kV Transformer):-**

2 Nos 33kV, 1250 A Vacuum Circuit Breaker suitable for Symmetrical Breaking Capacity of 31.5kA for 3 second comprising the following (Each Panel)

Sl.No	Description	Qty.	Recommended make
1.	<b>Circuit Breaker</b> Vacuum Interrupters 3Nos. Manual charged spring closing mechanism Motor operated closing mechanism 230 V AC Set of 6 NO + 6 NC Auxiliary contacts Shunt Trip coil suitable for 110 V DC Manual close Push Button Electrical Release for close, rated 110 V DC Mechanical ON/OFF Indicator	1set	ABB/ALSTOM SIEMENS/ CROMPTON GREAVES/BEL for Vacuum Interrupters
2	Breaker Control switch	1	KAYCEE/RECOM/SWITRON
3	LOCAL/REMOTE Switch	1	KAYCEE/RECOM/SWITRON
4	4 Core Current Transformers of ratio 600/300/5-5-1-1 A with output and accuracy class as follows. Core 1 : 15 VA / 5 P10 Core 2 : 15 VA / 0.2 S Core 3 : PS Core 4 : PS	3	ECS/Pragati/Gemini/CG/ ABB/Intrans/Resitech/ Vidyuth

**TECHNICAL SPECIFICATION**

**33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS**

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

5	Potential transformer, 3 phase star connected for transformer ratio 33kV/√3-110V/√3, output 100 VA, class 0.2, connected to the cable side mounted above the panel suitable for measuring incoming voltage complete with HV fuses and LV fuses.	1set	ECS/Pragati/Gemini/CG/ABB/Intrans/Resitech/Vidyuth
6	Ammeter 0-600A and 0-300A, 96 sq. mm. double scaled	3	AE/MECO/IMP/RISHAB/Superior
7	Digital voltmeter 0-40 kV, 48 x 96 mm, 3 1/2 digit LED display, self powered, class 0.5,	3	AE/MECO/IMP/RISHAB
8	TOD meter , Accuracy 0.2S	1	L&T/SECURE
9	Numerical REF Relay with Stabilising resistor (Variable 0-1000 Ohm) & Metrosil	1 set	ABB/ALSTOM/GE/SIEMENS -Siprotech /SEL/SCHNEIDER-MICOM
10	5 A, Numerical IDMT/DT draw-out type relay with 3 over current and 1 earth fault, NI with high set (As per Clause 20 of Annexure-I, Part-II)	1 set	ABB/ALSTOM/GE/SIEMENS -Siprotech/SEL/SCHNEIDER- MICOM
11	Master trip relay	1	ABB/ALSTOM/GE/SIEMENS -Siprotech
12	Inter trip relay	1	ABB/ALSTOM/GE/SIEMENS -Siprotech
13	TC Supervision relay	1	ABB/ALSTOM/GE/SIEMENS -Siprotech
14	DC Supply Supervision relay	1	ABB/ALSTOM/GE/SIEMENS -Siprotech
15	Breaker 'ON' RED indicating lamp	1	DAV/TEKNIC/ESSEN
16	Breaker 'OFF' GREEN indicating lamp	1	
17	'Spring Charged' BLUE indicating lamp	1	
18	'AUTO TRIP' AMBER indicating lamp	1	
19	'DC control supply fail' Yellow indicating lamp	1	
20	'Service Position' Blue indicating lamp	1	
21	'Test Position' White indicating lamp	1	
22	'Trip Circuit Healthy' White indicating lamp	1	
23	ON/OFF switch for Spring charging motor	1	KAYCEE/RECOM/SWITRON
24	AC outlet socket.	1	ANCHOR



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

25	Control Circuit MCBs	set	BUSSMAN/Schneider
26	Space heater with thermostat and control Switch	1 set	Girish/APTS
27	Panel illumination lamp	1	PHILIPS/BAJAJ
28	TTB for TOD meter	1	KAYCEE/AE
29	Micro processor based, facia annunciator 3Rx6C windows, with hooter, bell, accept, reset etc. assembly	1 set	ALAN/BHARANI
30	Terminal Block 1100V Grade	1 set	Elmex /Connectwell
31	Outdoor resin cast Neutral CT ratio 600/300-1A PS Class,Vkp 650V@ lower rate Rct 2.5 ohms @ 75 C, Imag @ Vkp/2 30-40 mA	1	ECS/Pragati/Gemini/CG/ ABB/Intrans/Resitech/ Vidyuth ( Type test report to be submitted with tender)
32	Capacitive Voltage indicator for monitoring whether the Cable is Live or Dead	1 set	ECS/NPT
33	Emergency Push button	1	DAV/TEKNIC/ESSEN

**\* Only recommended makes of Relays, Energy Meter and Vacuum Interrupter Bottles are acceptable. For other items, makes other than recommended ones are subject to approval of purchasing authority during drawing approval subject to verification of type test reports.**

Incomer Panels (Secondary side of 110/33 kV Transformer) Annunciator Facia Arrangement:

O/C TRIP	E/F TRIP	REF TRIP	DC SUPPLY FAIL	TRIP RECEIVED FROM 110 KV	TRIP CIRCUIT FAULTY
SPARE	SPARE	SPARE	SPARE	SPARE	AC SUPPLY FAIL

**c) Feeder Panel (Outgoing) :-** 2 Nos. with 33kV, 1250A Vacuum Circuit Breaker suitable for Symmetrical Breaking Capacity of 31.5kA for 3 second comprising the following (Each Panel)

Sl. No.	Description	Qty.	Recommended make
1.	<b>Circuit Breaker</b> Vacuum Interrupters 3Nos. Manual charged spring closing mechanism Motor operated closing mechanism 230V AC	1 set	ABB/ALSTOM



**TECHNICAL SPECIFICATION**

**33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS**

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

	Set of 6 NO + 6 NC Auxiliary contacts Shunt Trip coil suitable for 110 V DC Manual CLOSE/OPEN Push Button Electrical Release for close, rated 110 V DC Mechanical ON/OFF Indicator		SIEMENS/ CROMPTON GREAVES/BEL for Vacuum Interruption
2	Breaker Control switch	1	KAYCEE/RECOM/SWITRON
3	LOCAL/ REMOTE Switch	1	KAYCEE/RECOM/SWITRON
4	2 Core Current Transformers of ratio 300/5-5A with output and accuracy class as follows.  Core 1 : 15 VA / 5 P10 Core 2 : 15 VA / 0.2 S	3	ECS/Pragati/Gemini/CG/ ABB/Intrans/Resitech/ Vidyuth
5	Ammeter 0-300A , 5A ,class 0.5 96 sq. mm. double scaled	3	AE/MECO/IMP/RISHAB
6	TOD meter, Accuracy 0.2S	1	L&T/SECURE
7	Breaker 'ON' RED indicating lamp	1	DAV/TEKNIC/Essen
8	Breaker 'OFF' GREEN indicating lamp	1	
9	'Spring Charged' BLUE indicating lamp	1	
10	'AUTO TRIP' AMBER indicating lamp	1	
11	'DC control supply fail' Yellow indicating lamp	1	
12	'Service Position' Blue indicating lamp	1	
13	'Test Position' White indicating lamp	1	
14	'Trip Circuit Healthy' White indicating lamp	1	
15	PT Supply R Y B RED YELLOW BLUE indicating lamp	1 set	
16	5 A, Numerical IDMT/DT draw-out type relay with 3 over current and 1 earth fault ,NI with high set (As per Clause-20 of Annexure-I, Part- II)	1	ABB/ALSTOM/GE/ SIEMENS -Siprotech /SEL/SCHNEIDER -MICOM
17	Master trip relay	1	ABB/ALSTOM/GE/ SIEMENS -Siprotech
18	TC Supervision relay	1	ABB/ALSTOM/GE/ SIEMENS -Siprotech
19	DC Supply Supervision relay	1	ABB/ALSTOM/GE/ SIEMENS -Siprotech
20	ON/OFF switch for Spring charging motor	1	KAYCEE/RECOM/SWITRON
21	AC outlet socket.	1	ANCHOR/Superior
22	Control Circuit MCBs	set	BUSSMAN/Schneider
23	Space heater with thermostat & control switch	1 set	Girish/APTS

**TECHNICAL SPECIFICATION**

**33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS**

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

24	Panel illumination lamp	1 set	PHILIPS/BAJAJ/Superior
25	TTB for TOD meter	1	IMP/AE/Superior
26	Terminal Block 1100V Grade	1 set	Elmex /Connectwell
27	Capacitive Voltage indicator for monitoring whether the Cable is Live or Dead	1 set	ECS/NPT
28	Emergency Pushbutton	1	DAV/TEKNIC/ESSEN

Feeder Panel (Outgoing) Annunciator Facia Arrangement:

O/C TRIP	E/F TRIP	TRIP CIRCUIT FAULTY	DC SUPPLY FAIL	AC SUPPLY FAIL	SPARE
SPARE	SPARE	SPARE			

- d) Bus Coupler Panel:-** 1 No. with 33kV, 1250 A Vacuum Circuit Breaker suitable for Symmetrical Breaking Capacity of 31.5 kA for 3 second comprising the following

Sl. No.	Description	Qty.	Recommended make
1.	Vacuum Interrupters 3Nos. Manual charged spring closing mechanism Motor operated closing mechanism 230V AC Set of 6 NO + 6 NC Auxiliary contacts Shunt Trip coil suitable for 110 V DC Manual CLOSE/OPEN Push Button Electrical Release for close, rated 110 V DC Mechanical ON/OFF Indicator	1set	ABB/ALSTOM SIEMENS/ CROMPTON GREAVES/BEL for Vacuum Interrupters
2	Breaker Control switch	1	KAYCEE/RECOM/SWITRON
3	PT Selection relays for providing selected PT voltages to Outgoing feeders	1	ABB/ALSTOM/GE/ SIEMENS -Siprotech
4	RED 'ON' indicating lamp	1	DAV/TEKNIC/ESSEN
5	GREEN 'OFF' indicating lamp	1	
6	AMBER 'AUTO TRIP' indicating lamp	1	
7	BLUE "DC healthy" indicating lamp	1	

**TECHNICAL SPECIFICATION**

**33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS**

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

8	WHITE 'TC Healthy' indicating lamp	1	
9	BLUE 'Spring Charged' indicating lamp	1	
10	TC Supervision relay	1	ABB/ALSTOM/GE/ SIEMENS -Siprotech
11	DC Supply Supervision relay		ABB/ALSTOM/GE/ SIEMENS -Siprotech
12	ON/OFF switch for Spring charging motor	1	KAYCEE/ RECOM/ SWITRON
13	AC outlet socket.	1	ANCHOR
14	Control Circuit MCBs	set	BUSSMAN/Schneider
15	Space heater with thermostat and control Switch	1 set	Girish/APTS
16	Panel illumination lamp	1	PHILIPS/BAJAJ
17	1 Core Current Transformers of ratio 300/1A with PS Class	1 Set	ECS/Pragati/Gemini/CG/ABB/Intrans/ Resitech/ Vidyuth
18	Analog Voltmeter 0-36kV, 110V AC, class 0.5 96 sq. mm. double scaled	1	AE/ MECO/ IMP/ RISHAB
19	TOD meter, Accuracy 0.2S	1	L&T/ SECURE
20	'DC control supply fail' Yellow indicating lamp	1	
21	'Service Position' Blue indicating lamp	1	
22	'Test Position' White indicating lamp	1	
23	PT Supply R Y B RED YELLOW BLUE indicating lamp	1 set	
24	Numerical Busbar protection Relay	2	ABB/ALSTOM/GE/SIEMENS - Siprotech /SEL/ SCHNEIDER-MICOM
25	Master trip relay	2	ABB/ALSTOM/GE/ SIEMENS -Siprotech
26	ON/OFF switch for Spring charging motor	1	KAYCEE/RECOM/SWITRON
27	AC outlet socket.	1	ANCHOR/Superior
28	Control Circuit MCBs	set	BUSSMAN/Schneider



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**    Rev.#: 0    Effective Date-**21/04/2021**

29	TTB for TOD meter	1	IMP/AE/Superior
30	Terminal Block 1100V Grade	1 set	Elmex /Connectwell
31	Capacitive Voltage indicator for monitoring whether the Cable is Live or Dead	1 set	ECS/NPT
32	Emergency Push button	1	DAV/TEKNIC/ESSEN

Bus Coupler / Bus raiser panel Annunciator Facia Arrangement:

FDR-1 O/C TRIP	FDR-1 E/F TRIP	FDR-1 TRIP CKT FAULTY	FDR-1 DC SUPPLY FAIL	FDR-1 AC SUPPLY FAIL	FDR-2 O/C TRIP
FDR-2 E/F TRIP	FDR-2 TRIP CKT FAULTY	FDR-2 DC SUPPLY FAIL	FDR-2 AC SUPPLY FAIL	INCOMER-1 O/C TRIP	INCOMER-1 E/F TRIP
INCOMER-1 REF TRIP	INCOMER-1 HV TO LV INTER TRIP	INCOMER-1 TRIP CKT FAULTY	INCOMER-1 DC SUPPLY FAIL	INCOMER-1 AC SUPPLY FAIL	INCOMER-2 REF TRIP
INCOMER-1 O/C TRIP	INCOMER-1 E/F TRIP	INCOMER-1 HV TO LV INTER TRIP	INCOMER-1 TRIP CKT FAULTY	INCOMER-1 DC SUPPLY FAIL	INCOMER-1 AC SUPPLY FAIL
SECTION-1 BUS BAR PROTN. TRIP	SECTION-2 BUS BAR PROTN. TRIP	BUS COUPLER TRIP CKT FAULTY	BUS COUPLER DC SUPPLY FAIL	BUS COUPLER AC SUPPLY FAIL	FDR-1 O/C TRIP
FDR-1 E/F TRIP	FDR-1 TRIP CKT FAULTY	FDR-1 DC SUPPLY FAIL	FDR-1 AC SUPPLY FAIL	SPARE	SPARE
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE
SPARE	SPARE	SPARE	SPARE	SPARE	SPARE

**e) Cable Earthing truck – 1no.**

**f) Bus Earthing truck -1 no.**

**Any item though not specifically mentioned above, but necessary for operation and maintenance of the equipment as per technical requirements / standards are within the scope of the contract.**

**TECHNICAL SPECIFICATION**

**33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS**

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

**(2) SCHEDULE OF EQUIPMENTS for 3 Panel Sets:- Each set of 33kV, 1500 MVA 3 Panel Switch Board with Vacuum Circuit Breakers consisting of following:**

**a) Main Bus Bar Rating : 1250 A, 33kV**

**b) Feeder Panel (Incomer) : 1 No.**

with 33kV, 1500 MVA 1250A Vacuum Circuit Breaker suitable for Symmetrical Breaking Capacity of 25 kA for 3 sec. comprising the following:

Sl. No.	Description	Qty.	Recommended make
1.	<b>Circuit Breaker</b> Vacuum Interrupters 3Nos. Manual charged spring closing mechanism Motor operated closing mechanism 230V AC Set of 6 NO + 6 NC Auxiliary contacts Shunt Trip coil suitable for 110 V DC Manual CLOSE/OPEN Push Button Electrical Release for close, rated 110 V DC Mechanical ON/OFF Indicator	1set	ABB/ALSTOM SIEMENS/ CROMPTON GREAVES/BEL for Vacuum Interrupters
2	Breaker Control switch	1	KAYCEE/RECOM/SWITRON
3	LOCAL/ REMOTE Switch	1	KAYCEE/RECOM/SWITRON
4	2 Core Current Transformers of ratio 400-200/5-5A with output and accuracy class as follows.  Core 1 : 15 VA / 5 P10 Core 2 : 15 VA / 0.2 S	3	ECS/Pragati/Gemini/CG/ ABB/Intrans/Resitech/ Vidyuth
5	Potential transformer, 3 phase star connected for transformer ratio 33kV/ $\sqrt{3}$ -110V/ $\sqrt{3}$ , output 100 VA, class 0.2, connected to the cable side mounted above the panel suitable for measuring incoming voltage complete with HV fuses and LV fuses.	1set	ECS/Pragati/Gemini/CG/ ABB/Intrans/Resitech/ Vidyuth
6	Ammeter 0-400A and 0-200A, 5A ,class 0.5 96 sq. mm. double scaled	3	AE/MECO/IMP/RISHAB
7	Digital voltmeter 0-40 Kv,48 x96 mm ,31/2 digit LED display , self powered, class 0.5,	3	AE/MECO/IMP/RISHAB
8	TOD meter, Accuracy 0.2S		L&T/SECURE
9	Breaker 'ON' RED indicating lamp	1	DAV/TEKNIC/Essen

**TECHNICAL SPECIFICATION**

**33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS**

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

10	Breaker 'OFF' GREEN indicating lamp	1	
11	'Spring Charged' BLUE indicating lamp	1	
12	'AUTO TRIP' AMBER indicating lamp	1	
13	'DC control supply fail' Yellow indicating lamp	1	
14	'Service Position' Blue indicating lamp		
15	'Test Position' White indicating lamp	1	
16	'Trip Circuit Healthy' White indicating lamp		
17	PT Supply R Y B RED YELLOW BLUE indicating lamp	1 set	
18	5A, Numerical IDMT/DT relay with 3 over current and 1 earth fault.	1	ABB/ALSTOM/GE/SIEMENS /SEL/SCHNEIDER -MICOM/CG -AEGIS F
19	Master trip relay	1	ABB/ALSTOM/GE/SIEMENS
20	TC Supervision relay	1	ABB/ALSTOM/GE/SIEMENS
21	DC Supply Supervision relay		ABB/ALSTOM/GE/SIEMENS
22	ON/OFF switch for Spring charging motor	1	KAYCEE/RECOM/SWITRON
23	AC outlet socket.	1	ANCHOR/Superior
24	Control Circuit MCBs	set	BUSSMAN/Schneider
25	Space heater with thermostat & control switch	1 set	Girish/APTS
26	Panel illumination lamp	1	PHILIPS/BAJAJ/Superior
27	TTB for TOD meter	1	IIMP/DAV/AE/JVS
28	Terminal Block 1100V Grade	1 set	Elmex /Connectwell
29	Capacitive Voltage indicator for monitoring whether the Cable is Live or Dead	1 set	ECS/NPT
30	Emergency Pushbutton	1	DAV/TEKNIC/ESSEN

**c) Transformer Panels (Outgoing) : 2 Nos**

with 33kV, 1500 MVA 1250A Vacuum Circuit Breaker suitable for Symmetrical Breaking Capacity of 25kA for 3 sec. comprising the following (in each Panel)

**TECHNICAL SPECIFICATION**

**33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS**

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

Sl.No	Description	Qty.	Recommended make
1.	<b>Circuit Breaker</b> Vacuum Interrupters 3Nos. Manual charged spring closing mechanism Motor operated closing mechanism 230 V AC Set of 6 NO + 6 NC Auxiliary contacts Shunt Trip coil suitable for 110 V DC Manual close Push Button Electrical Release for close, rated 110 V DC Mechanical ON/OFF Indicator	1set	ABB/ALSTOM SIEMENS/ CROMPTON GREAVES/BEL for Vacuum Interrupters
2	Breaker Control switch	1	KAYCEE/RECOM/SWITRON
3	LOCAL/REMOTE Switch	1	KAYCEE/RECOM/SWITRON
4	3 Core Current Transformers of ratio 200/100/5-5-1A with output and accuracy class as follows.  Core 1 : 15 VA / 5 P10 Core 2 : 15 VA / 0.2 S Core 3 : PS	3	ECS/Pragati/Gemini/CG/ ABB/Intrans/Resitech/ Vidyuth
5	Ammeter 0-200A and 0-100A, 96 sq. mm. double scaled	3	AE/MECO/IMP/RISHAB/ Superior
6	TOD meter , Accuracy 0.2S		L&T/SECURE
7	Numerical REF Relay with Stabilising resistor (Variable 0-1000 Ohm)& Metrosil	1	ABB/ALSTOM/GE/ SIEMENS /SEL/ SCHNEIDER-MICOM
8	Numerical IDMT/DT draw-out type relay with 3 over current and 1 earth fault, NI with high set .	1	ABB/ALSTOM/GE/ SIEMENS /SEL/ SCHNEIDER- MICOM/CG- AEGIS F
9	Master trip relay	1	ABB/ALSTOM/GE/ SIEMENS
10	Inter trip relay	1	ABB/ALSTOM/GE/ SIEMENS
11	TC Supervision relay	1	ABB/ALSTOM/GE/ SIEMENS
12	DC Supply Supervision relay	1	ABB/ALSTOM/GE/ SIEMENS
13	Auxiliary relay for transformer TRIP, ALARM functions 30ABCD, 30EFGH	2	ABB/ALSTOM/GE/ SIEMENS
14	Breaker 'ON' RED indicating lamp	1	DAV/TEKNIC/ESSEN
15	Breaker 'OFF' GREEN indicating lamp	1	



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

16	'Spring Charged' BLUE indicating lamp	1	
17	'AUTO TRIP' AMBER indicating lamp	1	
18	'DC control supply fail' Yellow indicating lamp	1	
19	'Service Position' Blue indicating lamp	1	
20	'Test Position' White indicating lamp	1	
21	'Trip Circuit Healthy' White indicating lamp	1	
22	ON/OFF switch for Spring charging motor	1	KAYCEE/RECOM/SWITRON
23	AC outlet socket.	1	ANCHOR
24	Control Circuit MCBs	set	BUSSMAN/Schneider
25	Space heater with thermostat and control Switch	1 set	Girish/APTS
26	Panel illumination lamp	1	PHILIPS/BAJAJ
27	TTB for TOD meter	1	IMP/DAV/AE/JVS
28	Micro processor based, facia annunciator 3Rx6C windows, with hooter, bell, accept, reset etc. assembly	1 set	ALAN/BHARANI
29	Terminal Block 1100V Grade	1 set	Elmex /Connectwell
30	Outdoor resin cast Neutral CT ratio 200/100-1A PS Class,Vkp 300V@ lower rate Rct 2.5 ohms @ 75 C, Imag @ Vkp/2 30-40 mA	1	ECS/Pragati/Gemini/CG/ ABB/Intrans/Resitech/ Vidyuth ( Type test report to be submitted with tender)
31	Capacitive Voltage indicator for monitoring whether the Cable is Live or Dead	1 set	ECS/NPT
32	Emergency Pushbutton	1	DAV/TEKNIC/ESSEN

**\* Only recommended makes of Relays, Energy Meter and Vacuum Interrupter Bottles are acceptable. For other items, makes other than recommended ones are subject to approval of purchasing authority during drawing approval subject to verification of type test reports.**

#### TRANSFORMER PANEL ANNUNCIATOR FACIA ARRANGEMENT:

O/C TRIP	E/F TRIP	REF TRIP	LBB OPRTD	TRIP RECEIVED FROM 11 KV	FR. BUCHOL TRIP
WINDING TEMP	TFR. LOW OIL LEVEL	TRIP CIRCUIT	SPARE	SPARE	TFR. BUCHOLZ



**TECHNICAL SPECIFICATION**

**33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS**

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

TRIP		FAULTY			ALARM
WINDING TEMP ALARM	OIL TEMP ALARM	SPARE	SPARE	DC SUPPLY FAIL	AC SUPPLY FAI

**d) Cable Earthing truck – 1no.**

**e) Bus Earthing truck -1 no.**

**Any item though not specifically mentioned above, but necessary for operation and maintenance of the equipment as per technical requirements / standards are within the scope of the contract.**

**36. (a) LIST OF SPARES TO BE PROVIDED (For each 5 Panel Set):-**

SI.No	DESCRIPTION	QTY
1	CB Closing & Tripping coil	2 set
2	CB Truck assembly complete	1 set
3	Bus bar supporting insulator	6 Nos
4	CB Auxiliary contact	1 set
5	3 O/C + 1 E/F Relay	2
6	Master trip relay	2
7	LED Indicating lamp assembly	12 Nos
8	CT suitable for outgoing feeder panel	3 Nos
9	CT suitable for incomer panel	3 Nos
10	PT single pole with fuse	3 nos.
11	PT Fuse	6 nos.

**(b) LIST OF SPARES TO BE PROVIDED (For each 3 Panel Set):-**

SI.No	DESCRIPTION	QTY
1	CB Closing & Tripping coil	2 set
2	CB Truck assembly complete	1 set
3	Bus bar supporting insulator	6 Nos
4	CB Auxiliary contact	1 set
5	3 O/C + 1 E/F Relay	1
6	Master trip relay	1
7	LED Indicating lamp assembly	12 Nos
8	CT suitable for feeder panel	3 Nos
9	CT suitable for transformer panel	3 Nos
10	PT single pole with fuse	3 nos.
11	PT Fuse	3 nos.



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

Sd/-

**CHIEF ENGINEER (SCM)**



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

### Annexure – I (A)

#### SCHEDULE OF GUARANTEED TECHNICAL PARTICULARS FOR 33KV INDOOR VCB SWITCHGEAR 5 PANEL SET

(Technical Particulars of Type Tested item / model which is offered as per the technical specification of this tender shall be furnished)

Sl. No.	Description	
<b>1</b>	<b>PANEL DETAILS</b>	
a	Mak	
b	Type Designation	
c	Applicable Standards	
d	Details of separate compartments provided.	
e	Compartments for which Pressure relief valves provided	
<b>2</b>	<b>VOLTAGE RATINGS</b>	
a	Rated Voltage & Frequency	
b	Power Frequency Withstand voltage	
c	Impulse withstand voltage	
<b>3</b>	<b>CURRENT RATINGS</b>	
a	Normal Current rating	
b	Short time current rating 3 second	
c	Short time current rating 1 second	
d	Short Circuit Making Current	
e	Rupturing capacity	
<b>4</b>	<b>CONSTRUCTION</b>	
a	Partition Class	
b	Loss of Service Continuity Class	
c	Degree of Protection	
d	Whether satisfying Intenal Arc Classification IAC AFLR 25kA, 1 sec.	
e	Operating Speed of breaker in meter per sec.	

**TECHNICAL SPECIFICATION**

**33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS**

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

f	Minimum distance between live parts and earthed metals (in mm)	
g	Minimum distance between Phase (in mm)	
h	Power to trip breaker Electrically at 110V	
i	Type of contact (Main & Auxiliary)	
j	Type of bushing / insulator (indicate creepage distance in mm)	
k	Dry flashover in kV (rms)	
l	Travel of contact in mm	
m	Material of insulation between break poles	
n	Impulse flash over in kV (Peak)	
o	Estimated puncture value of insulator in kV	
p	Drive mechanism employed between operating mechanism	
q	Weight of complete three phase breaker with operating mechanism bushing & frame work	
r	Thickness of sheet metal used for panels in mm	
s	Whether seven tank processing done as per spec , on sheet metal.	
t	Type of finishing paint	
u	Thickness of powder coating	
v	No. of Mechanical Operations	
w	Closing/ Tripping coil Supply	



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

x	Spring Charging Motor Supply	
y	Auxiliary Contacts	
z	Whether E2 M2 C2 compliant as per spec & Type test report submitted?	
<b>5</b>	<b>VCB</b>	
a	Make of Interrupter	
b	Type Designation	
c	Rated Current	
d	Applicable Standard	
e	Operating Sequence (Duty cycle)	
f	Opening Time (ms)	
g	Break Time (ms)	
h	Contact resistance	
i	Whether VCB is fully encapsulated	
j	Life expectancy under normal condition (in years)	
k	Whether Type Test Report Submitted	
<b>6</b>	<b>PANEL SHELL</b>	
a	Make	
b	Dimension (WxDxH) in mm	

**TECHNICAL SPECIFICATION**

**33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS**

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

c	Height of Panel alone in mm		
d	Height of Panel with Internal Arc Routing Baffles (in mm)		
e	Height of Panel with closed pressure relief duct (in mm)		
f	Clearance required on Front, Rear, Right and Left for operation of equipment (in mm)		
g	Clearance required on Front, Rear, Right and Left for replacement of equipment (in mm)		
h	Panel weight (in Kg)		
i	Panel weight including Packing (Kg)		
<b>7</b>	<b>Current Transformer</b>		
a	Make		
b	Type , Model No.		
c	Ratio		
d	Class of Accuracy/VA 1) Bus Coupler 2) Incoming Feeder 3) Outgoing Feeder		
e	Continuous percent overload		
f	1 Sec. Over-current rating		
g	Knee point voltage (min)		
h	Maximum exciting current		
i	Class of Insulation E or better		



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

j	Whether CT Secondary terminals are easily accessible for testing by removing back door.		
k	Whether Type Test Report Submitted		
7	Potential Transformer		
a	Make		
b	Type & Model No.		
c	Ratio		
d	Rated burden (VA per phase)		
e	Class of Accuracy		
f	PT Location		
g	Whether Withdrawable type , furnish details		
h	PT Fuse type, Make,rating, replacement details, etc		
i	Whether Type Test Report Submitted		
8	<b>NEUTRAL CT</b>		
a	Make		
b	Type: Cast Resin/ Oil		
c	Class of Insulation		
d	Model No:		
e	Ratio		
f	Class of Accuracy		
g	Minimum Knee Point Voltage		
h	Maximum excitation current at $V_k/2$		



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

i	Secondary Resistance at 75°C.		
j	Whether Type Test Report Submitted		
<b>9</b>	<b>BUS BAR</b>		
a	Material		
b	Size of Main Bus & Current Density		
c	Current Rating of Bus		
d	Short time current rating		
e	Size of Dropper & Current density		
f	Current rating of Dropper		
g	HT Sleeve : make		
h	Whether Bus Bar Supported or self supported.		
i	Bus Bar Support material		
j	Whether PVC Sleeve used		
k	Confirm that for bus bar joints, dropper connections and CT connections, there shall be minimum four bolts per joint.		
<b>10</b>	<b>INDICATING LAMPS</b>		
a	Make		
b	Type / Model & body material		





## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

c	Operating Voltage (Volts)		
d	Size of lens (mm)		
e	Wattage of LEDs(Watts)		
f	Colour of LED covers		
g	LED Replacement method		
h	Whether Series connected Resistance provided		
i	Whether Integral engraved plate provided.		
<b>11</b>	<b>SPACE HEATER/ THERMOSTAT</b>		
a	Make of space heater		
b	Rating V, Hz, W		
c	Thermostat Make		
d	Thermostat Rated Voltage, Temp Setting Range		
<b>12</b>	<b>TEST BLOCK</b>		
a	Make ( For Energy Meter)		
b	Type / Model ( For Energy Meter)		
c	Make ( For Relays)		
d	Type/ Model ( For Relays)		
<b>13</b>	<b>PUSH BUTTON</b>		
a	Make		



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

b	Type(Microprocessor Based or not) /Model		
c	Body/ Case : Metallic or not		
d	Contact Type (Momentary/ Maintained)/Material		
e	Whether shrouding provided to prevent in advertent operations?		
f	Number of No/NC Contacts		
g	Making / Carry Current		
h	Breaking Current		
<b>14</b>	<b>Interior Lighting and Receptacle</b>		
a	Interior lighting make/Type/ Rating		
b	Whether Door Switch for light provided/ Make/Type		
c	Universal Multi pin socket (15A) Make/ Rating		
d	Whether ISI marked		
<b>15</b>	<b>Fuses and MCB</b>		
a	Make of MCB		
b	Whether MCB is ISI marked		
c	Make of Fuse/ Links		
d	Whether Fuses are ISI marked		



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

<b>16</b>	<b>Annunciation System (Micro controller based)</b>		
a	Make		
b	Type and Model No.		
c	No. of Windows & window dimension in mm		
d	Dimension (LxWxD) in mm		
e	Supply Voltage		
f	Permissible Voltage variation		
g	Power Consumption per window		
h	Fault input contact (Potential Free NO/NC)		
i	Minimum duration of impulse for initiating contact		
j	Contact Rating of auxiliary relay provided.		
k	Flickering speed of windows		
l	Whether AC Failure and DC Failure feature included		
m	Is the sequence of operation as per specification		
n	Push Buttons for Emergency/ Warning test: Integral or External.		
o	Buzzer/ Hooter: Integral or External- If external they shall be provided		
<b>17</b>	<b>EARTHING</b>		



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

a	Size of Earth Bus Bar		
b	Material of Earth Bar		
c	Conductor size for earth connection from body of component devices		
d	Colour of earthing wire		
<b>18</b>	<b>PANEL WIRING</b>		
a	Name of Cable Manufacturer		
b	Type and Designation of Cable		
c	Conforming Standard		
d	Whether PVC insulated FRLS cable used		
e	Voltage Grade of Cable		
f	No. of Cores/ Stranded or not/ Tinned Copper or not		
g	Size of conductor for Auxiliary AC Supply		
h	Size of conductor for CT /PT/DC Aux. Circuit		
i	Size of conductor for other Circuits		
j	Type of terminals provided on wiring		
<b>19</b>	<b>TERMINAL BLOCK</b>		
a	Name of Manufacturer		



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

b	Type and Model of Terminal Block		
c	Type and Model of Terminal Block for PT		
d	Type and Model of Terminal Block for CT		
e	Conforming Standard		
f	Voltage Grade (1100V required)		
g	Continuous Current Rating in A		
h	Material used		
i	Maximum no. of cables that can be connected		
j	% & Number of spare terminals provided		
k	Transparent removable covers provided or not		
<b>20</b>	<b>NAME PLATE AND MARKINGS</b>		
a	Material of Name Plate & Colour		
b	Letters Punched or Engraved		
c	Whether Identification label as per specification provided.		
<b>21</b>	<b>CIRCUIT BREAKER CONTROL SWITCH</b>		
a	Make		



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

b	Model		
c	Whether Spring Return to Neutral with lost motion device and locking facility		
d	No. of positions		
e	Type of handle		
f	No. of ways in each position		
g	Making & Breaking capacity of contacts		
h	No. of mechanical operations		
i	Whether locking arrangement provided or not		
<b>22</b>	<b>LOCAL/REMOTE SELECTION SWITCH</b>		
a	Make		
b	Model		
c	Whether Stay put type		
d	No. of positions		
e	Type of handle		
f	No. of ways in each position		
g	Making & Breaking capacity of contacts		



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

h	No. of mechanical operations		
<b>23</b>	<b>Ammeter</b>		
a	Make		
b	Type & Model No.		
c	Conforming Standard		
d	Rated Current		
e	Size		
f	Accuracy		
g	CT Ratio		
h	Scale Ranges		
i	Additional Dial		
j	Burden		
<b>24</b>	<b>Voltmeter</b>		
a	Make		
b	Type & Model No.		
c	Conforming Standard		
d	Rated voltage/ Burden/ Accuracy		



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

e	Size		
f	Size of Digits/No. of Digits/No. of decimals		
g	Whether super bright LEDs used		
h	Maximum Value of Voltage Scale		
<b>25</b>	<b>TOD ENERGY METER</b>		
a	Make		
b	Model No.		
c	Type (3 ph, 3 Element, 4 wire)		
d	Accuracy		
e	Rated voltage/ Current		
f	VA Burden of CTs/PTs		
g	Display Parameters		
h	No. of modes of display		
i	Maximum No. of decimal places in Mode 3		
j	Whether retain last recorded reading in case of power failure/ Furnish details		
k	Whether display both import and export		
l	Whether having Data logging and data retrieving facility/ Furnish details		





## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

m	Temperature compensation provide or not		
n	Direct reading or use of Multiplication factor required/ If required MF		
o	No. of Digits provided and whether sufficient for 1000 hrs of operation/Furnish details		
p	Whether current coil have continuous overload capacity of 200% for both accuracy and thermal limits		
q	Whether current coil shall withstand at least 10 times the rated current for 0.5 second with out loss of accuracy		
r	Transmitting contacts available or not.  Impulse rate/ whether suitable for remote indicating or summation/Furnish details		
s	Communication port/ protocol/ data transfer rate Whether conforming to tender spec. / Furnish details.		
t	Whether DLMS compliant		
<b>26</b>	<b>3 OVERCURRENT &amp; EARTH FAULT RELAY</b>		
a	Make		
b	Model No.		
c	Type		
d	Current Rating		

**TECHNICAL SPECIFICATION**

**33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS**

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

e	Whether Separate LEDs provided for R,Y, B & E faults		
f	Whether IEC 61850 Compliant		
g	Communication Ports provided		
h	Whether self supervision facility provided.		
i	Characteristic curve		
j	TMS for IDMT O/C and E/F		
k	IDMT O/C Protection current setting		
l	IDMT E/F Protection current setting		
m	High Set (50 & 50N) current setting		
n	No. of Digital input/ Output		
o	No. of Events stored		
p	Whether Local Breaker Backup feature available and wired.		
q	No. of fault records stored		
r	No. of voltage inputs in Relay (3 nos. required)		
s	Whether Type Test report submitted?		
<b>27</b>	<b>REF RELAY</b>		
a	Make		



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

b	Model No.		
c	Type: Numerical , High Impedance		
d	Current Rating & Aux Voltage		
e	Type of indicator resetting facility		
f	Operating time (ms)		
g	Setting Range		
h	Contacts		
i	Variable Stabilising Resistor value (Ω)/Wattage(W), Make		
j	Details of Metrosil provided Make, Rating, Model No.		
l	Communication Ports provided		
k	Whether REF relay is wired to initiate disturbance recorder of 3 over current earth fault relay in the event of operation?		
l	Whether Type Test report of Relay submitted?		
<b>28</b>	<b>Busbar Protection Relay</b>		
a	Make		
b	Model No.		
c	Type: Numerical , High Impedance		
d	Current Rating & Aux Voltage		
e	Type of indicator resetting facility		
f	Operating time (ms)		



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

g	Setting Range		
h	Contacts		
i	Variable Stabilising Resistor value ( $\Omega$ )/Wattage(W), Make		
j	Details of Metrosil provided Make, Rating, Model No.		
l	Communication Ports provided		
k	Whether relay is wired to initiate disturbance recorder of 3 over current earth fault relay in the event of operation?		
l	Whether Type Test report of Relay submitted?		
<b>29</b>	<b>Trip Circuit Supervision Relay</b>		
a	Makers name		
b	Type and Model Name		
c	Aux Voltage (Volts)		
d	Number of contacts		
e	Operating coil VA burden		
f	Making capacity of contacts		
g	Whether self reset type or hand reset type		
h	Draw out or non-drawout type		
i	Case finish		
<b>30</b>	<b>DC Supply Monitoring Relay</b>		
a	Make		



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

b	Type and Model Name		
c	Aux Voltage (Volts)		
d	Number of normally contacts	N0 / NC/Change Over	N0 / NC/Change Over
e	Operating coil VA burden		
f	Making capacity of contacts		
g	Whether self reset type or hand reset type		
h	Draw out or non-drawout type		
i	Case finish		
<b>31</b>	<b>High Speed Tripping Relay</b>		
a	Make		
b	Type and Model Name		
c	Aux Voltage (Volts)		
d	Number of normally contacts	N0 / NC /Change Over	N0 / NC/Change Over
e	Operating coil VA burden		
f	Whether High Impedance Type		
g	Whether self reset type or hand reset type		
h	Type of Flag indicator		
i	Operating Time		
j	Reset Time		
k	Draw out or non-drawout type		
l	Case finish		
<b>32</b>	<b>High Speed Inter Tripping Relay</b>		
a	Make		
b	Type and Model Name		



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

c	Aux Voltage (Volts)		
d	Number of normally contacts		
e	Operating coil VA burden		
f	Whether High Impedance Type		
g	Whether self reset type or hand reset type		
h	Type of Flag indicator		
i	Operating Time		
j	Reset Time		
k	Draw out or non-drawout type		
l	Case finish		
33	ON/OFF switch for Spring charging motor Make , Model & Rating		
34	TTB for TOD meter Make & Model No.		
35	Whether Removable HV Cable gland plate is provided with hole suitable for 3 core 400sq.mm XLPE cable?		
36	Capacitive Voltage indicator for monitoring whether the Cable is Live or Dead Make/ Model No.		
37	33kV Cable Termination Height from gland plate level.		
38	Maximum Closing Time of Circuit Breaker (ms)		
39	Maximum Opening Time of Circuit Breaker (ms)		



# SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

## TECHNICAL SPECIFICATION

### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

**Name and Address of Bidder**



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: SCM-SPEC/XM/3&5 Panel

Rev.#: 0

Effective Date-21/04/2021

### Annexure – I (B)

#### SCHEDULE OF GUARANTEED TECHNICAL PARTICULARS FOR 33KV INDOOR VCB SWITCHGEAR 3 PANEL SET

(Technical Particulars of Type Tested item / model which is offered as per the technical specification of this tender shall be furnished)

Sl. No.	Description	Particulars
<b>1</b>	<b>PANEL DETAILS</b>	
a	Make	
b	Type Designation	
c	Applicable Standards	
d	Details of separate compartments provided.	
e	Compartments for which Pressure relief valves provided	
<b>2</b>	<b>VOLTAGE RATINGS</b>	
a	Rated Voltage & Frequency	
b	Power Frequency Withstand voltage	
c	Impulse withstand voltage	
<b>3</b>	<b>CURRENT RATINGS</b>	
a	Normal Current rating	
b	Short time current rating 3 second	
c	Short time current rating 1 second	
d	Short Circuit Making Current	
e	Rupturing capacity	
<b>4</b>	<b>CONSTRUCTION</b>	
a	Partition Class	
b	Loss of Service Continuity Class	
c	Degree of Protection	
d	Whether satisfying Intenal Arc Classification IAC AFLR 25kA, 1 sec.	
e	Operating Speed of breaker in meter per sec.	





## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

f	Minimum distance between live parts and earthed metals (in mm)	
g	Minimum distance between Phase (in mm)	
h	Power to trip breaker Electrically at 110V	
i	Type of contact (Main & Auxiliary)	
j	Type of bushing / insulator (indicate creepage distance in mm)	
k	Dry flashover in kV (rms)	
l	Travel of contact in mm	
m	Material of insulation between break poles	
n	Impulse flash over in kV (Peak)	
o	Estimated puncture value of insulator in kV	
p	Drive mechanism employed between operating mechanism	
q	Weight of complete three phase breaker with operating mechanism bushing & frame work	
r	Thickness of sheet metal used for panels in mm	
s	Whether seven tank processing done as per spec , on sheet metal.	
t	Type of finishing paint	
u	Thickness of powder coating	
v	No. of Mechanical Operations	
w	Closing/ Tripping coil Supply	



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

x	Spring Charging Motor Supply	
y	Auxiliary Contacts	
z	Whether E2 M2 C2 compliant as per spec & Type test report submitted?	
<b>5</b>	<b>VCB</b>	
a	Make of Interrupter	
b	Type Designation	
c	Rated Current	
d	Applicable Standard	
e	Operating Sequence (Duty cycle)	
f	Opening Time (ms)	
g	Break Time (ms)	
h	Contact resistance	
i	Whether VCB is fully encapsulated	
j	Life expectancy under normal condition ( in years)	
k	Whether Type Test Report Submitted	
<b>6</b>	<b>PANEL SHELL</b>	<b>Feeder Panel (Incomer)</b>
a	Make	
b	Dimension (WxDxH) in mm	

**TECHNICAL SPECIFICATION**

**33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS**

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

c	Height of Panel alone in mm		
d	Height of Panel with Internal Arc Routing Baffles (in mm)		
e	Height of Panel with closed pressure relief duct (in mm)		
f	Clearance required on Front, Rear, Right and Left for operation of equipment (in mm)		
g	Clearance required on Front, Rear, Right and Left for replacement of equipment (in mm)		
g	Panel weight (in Kg)		
h	Panel weight including Packing (Kg)		
	<b>7 Current Transformer</b>		
a	Make		
b	Type , Model No.		
c	Ratio		
d	Class of Accuracy/VA		
e	Continuous percent overload		
f	1 Sec. Over-current rating		
g	Knee point voltage (min)		
h	Maximum exciting current		
i	Class of Insulation E or better		
j	Whether CT Secondary terminals are easily accessible for testing by removing back door.		
k	Whether Type Test Report Submitted		
	<b>7 Potential Transformer</b>		
a	Make		
b	Type & Model No.		

**TECHNICAL SPECIFICATION**

**33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS**

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

c	Ratio		
d	Rated burden (VA per phase)		
e	Class of Accuracy		
f	PT Location		
g	Whether Withdrawable type , furnish details		
h	PT Fuse type, Make,rating, replacement details, etc		
i	Whether Type Test Report Submitted		
<b>8</b>	<b>NEUTRAL CT</b>		
a	Make		
b	Type: Cast Resin/ Oil		
c	Class of Insulation		
d	Model No:		
e	Ratio		
f	Class of Accuracy		
g	Minimum Knee Point Voltage		
h	Maximum excitation current at $V_k/2$		
i	Secondary Resistance at 75°C.		
j	Whether Type Test Report Submitted		
<b>9</b>	<b>BUS BAR</b>		
a	Material		
b	Size of Main Bus & Current Density		
c	Current Rating of Bus		
d	Short time current rating		
e	Size of Dropper & Current density		
f	Current rating of Dropper		



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

g	HT Sleeve : make		
h	Whether Bus Bar Supported or self supported.		
i	Bus Bar Support material		
j	Whether PVC Sleeve used		
k	Confirm that for bus bar joints, dropper connections and CT connections, there shall be minimum four bolts per joint.		
<b>10</b>	<b>INDICATING LAMPS</b>		
a	Make		
b	Type / Model & body material		
c	Operating Voltage (Volts)		
d	Size of lens (mm)		
e	Wattage of LEDs(Watts)		
f	Colour of LED covers		
g	LED Replacement method		
h	Whether Series connected Resistance provided		
i	Whether Integral engraved plate provided.		
<b>11</b>	<b>SPACE HEATER/ THERMOSTAT</b>		
a	Make of space heater		
b	Rating V, Hz, W		
c	Thermostat Make		
d	Thermostat Rated Voltage, Temp Setting Range		
<b>12</b>	<b>TEST BLOCK</b>		
a	Make ( For Energy Meter)		
b	Type / Model ( For Energy Meter)		



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

c	Make ( For Relays)		
d	Type/ Model ( For Relays)		
<b>13</b>	<b>PUSH BUTTON</b>		
a	Make		
b	Type(Microprocessor Based or not) /Model		
c	Body/ Case : Metallic or not		
d	Contact Type (Momentary/ Maintained)/Material		
e	Whether shrouding provided to prevent in advertent operations?		
f	Number of No/NC Contacts		
g	Making / Carry Current		
h	Breaking Current		
<b>14</b>	<b>Interior Lighting and Receptacle</b>		
a	Interior lighting make/Type/ Rating		
b	Whether Door Switch for light provided/ Make/Type		
c	Universal Multi pin socket (15A) Make/ Rating		
d	Whether ISI marked		
<b>15</b>	<b>Fuses and MCB</b>		
a	Make of MCB		
b	Whether MCB is ISI marked		
c	Make of Fuse/ Links		
d	Whether Fuses are ISI marked		
<b>16</b>	<b>Annunciation System (Micro controller based)</b>		
a	Make		
b	Type and Model No.		



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

c	No. of Windows & window dimension in mm		
d	Dimension (LxWxD) in mm		
e	Supply Voltage		
f	Permissible Voltage variation		
g	Power Consumption per window		
h	Fault input contact (Potential Free NO/NC)		
i	Minimum duration of impulse for initiating contact		
j	Contact Rating of auxiliary relay provided.		
k	Flickering speed of windows		
l	Whether AC Failure and DC Failure feature included		
m	Is the sequence of operation as per specification		
n	Push Buttons for Emergency/ Warning test: Integral or External.		
o	Buzzer/ Hooter: Integral or External- If external they shall be provided		
<b>17</b>	<b>EARTHING</b>		
a	Size of Earth Bus Bar		
b	Material of Earth Bar		
c	Conductor size for earth connection from body of component devices		
d	Colour of earthing wire		
<b>18</b>	<b>PANEL WIRING</b>		
a	Name of Cable Manufacturer		
b	Type and Designation of Cable		
c	Conforming Standard		



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

d	Whether PVC insulated FRLS cable used		
e	Voltage Grade of Cable		
f	No. of Cores/ Stranded or not/ Tinned Copper or not		
g	Size of conductor for Auxiliary AC Supply		
h	Size of conductor for CT /PT/DC Aux. Circuit		
i	Size of conductor for other Circuits		
j	Type of terminals provided on wiring		
<b>19</b>	<b>TERMINAL BLOCK</b>		
a	Name of Manufacturer		
b	Type and Model of Terminal Block		
c	Type and Model of Terminal Block for PT		
d	Type and Model of Terminal Block for CT		
e	Conforming Standard		
f	Voltage Grade (1100V required)		
g	Continuous Current Rating in A		
h	Material used		
i	Maximum no. of cables that can be connected		
j	% & Number of spare terminals provided		
k	Transparent removable covers provided or not		
<b>20</b>	<b>NAME PLATE AND MARKINGS</b>		
a	Material of Name Plate & Colour		
b	Letters Punched or Engraved		





## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

c	Whether Identification label as per specification provided.		
<b>21</b>	<b>CIRCUIT BREAKER CONTROL SWITCH</b>		
a	Make		
b	Model		
c	Whether Spring Return to Neutral with lost motion device and locking facility		
d	No. of positions		
e	Type of handle		
f	No. of ways in each position		
g	Making & Breaking capacity of contacts		
h	No. of mechanical operations		
i	Whether locking arrangement provided or not		
<b>22</b>	<b>LOCAL/REMOTE SELECTION SWITCH</b>		
a	Make		
b	Model		
c	Whether Stay put type		
d	No. of positions		
e	Type of handle		
f	No. of ways in each position		
g	Making & Breaking capacity of contacts		
h	No. of mechanical operations		
<b>23</b>	<b>Ammeter</b>		
a	Make		



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

b	Type & Model No.		
c	Conforming Standard		
d	Rated Current		
e	Size		
f	Accuracy		
g	CT Ratio		
h	Scale Ranges		
i	Additional Dial		
j	Burden		
<b>24</b>	<b>Voltmeter</b>		
a	Make		
b	Type & Model No.		
c	Conforming Standard		
d	Rated voltage/ Burden/ Accuracy		
e	Size		
f	Size of Digits/No. of Digits/No. of decimals		
g	Whether super bright LEDs used		
h	Maximum Value of Voltage Scale		
<b>25</b>	<b>TOD ENERGY METER</b>		
a	Make		
b	Model No.		
c	Type (3 ph, 3 Element, 4 wire)		
d	Accuracy		
e	Rated voltage/ Current		
f	VA Burden of CTs/PTs		
g	Display Parameters		



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

h	No. of modes of display		
i	Maximum No. of decimal places in Mode 3		
j	Whether retain last recorded reading in case of power failure/ Furnish details		
k	Whether display both import and export		
l	Whether having Data logging and data retrieving facility/ Furnish details		
m	Temperature compensation provide or not		
n	Direct reading or use of Multiplication factor required/ If required MF		
o	No. of Digits provided and whether sufficient for 1000 hrs of operation/Furnish details		
p	Whether current coil have continuous overload capacity of 200% for both accuracy and thermal limits		
q	Whether current coil shall withstand at least 10 times the rated current for 0.5 second with out loss of accuracy		
r	Transmitting contacts available or not.  Impulse rate/ whether suitable for remote indicating or summation/Furnish details		
s	Communication port/ protocol/ data transfer rate Whether conforming to tender spec. / Furnish details.		
t	Whether DLMS compliant		
<b>26</b>	<b>3 OVERCURRENT &amp; EARTH FAULT RELAY</b>		
a	Make		



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

b	Model No.		
c	Type		
d	Current Rating		
e	Whether Separate LEDs provided for R,Y, B & E faults		
f	Whether IEC 61850 Compliant		
g	Communication Ports provided		
h	Whether self supervision facility provided.		
i	Characteristic curve		
j	TMS for IDMT O/C and E/F		
k	IDMT O/C Protection current setting		
l	IDMT E/F Protection current setting		
m	High Set (50 & 50N) current setting		
n	No. of Digital input/ Output		
o	No. of Events stored		
p	Whether Local Breaker Backup feature available and wired.		
q	No. of fault records stored		
r	No. of voltage inputs in Relay (3 nos. required)		
s	Whether Type Test report submitted?		
<b>27</b>	<b>REF RELAY</b>		
a	Make		
b	Model No.		
c	Type: Numerical , High Impedance		
d	Current Rating & Aux Voltage		
e	Type of indicator resetting facility		



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

f	Operating time (ms)		
g	Setting Range		
h	Contacts		
i	Variable Stabilising Resistor value ( $\Omega$ )/Wattage(W), Make		
j	Details of Metrosil provided Make, Rating, Model No.		
l	Communication Ports provided		
k	Whether REF relay is wired to initiate disturbance recorder of 3 over current earth fault relay in the event of operation?		
l	Whether Type Test report of Relay submitted?		
<b>28</b>	<b>Trip Circuit Supervision Relay</b>		
a	Makers name		
b	Type and Model Name		
c	Aux Voltage (Volts)		
d	Number of contacts	N0 / NC /Change Over	N0 / NC/Change Over
e	Operating coil VA burden		
f	Making capacity of contacts		
g	Whether self reset type or hand reset type		
h	Draw out or non-drawout type		
i	Case finish		
<b>29</b>	<b>DC Supply Monitoring Relay</b>		
a	Make		
b	Type and Model Name		



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

c	Aux Voltage (Volts)		
d	Number of normally contacts		
e	Operating coil VA burden		
f	Making capacity of contacts		
g	Whether self reset type or hand reset type		
h	Draw out or non-drawout type		
i	Case finish		
<b>30</b>	<b>High Speed Tripping Relay</b>		
a	Make		
b	Type and Model Name		
c	Aux Voltage (Volts)		
d	Number of normally contacts		
e	Operating coil VA burden		
f	Whether High Impedance Type		
g	Whether self reset type or hand reset type		
h	Type of Flag indicator		
i	Operating Time		
j	Reset Time		
k	Draw out or non-drawout type		
l	Case finish		
<b>31</b>	<b>High Speed Inter Tripping Relay</b>		
a	Make		
b	Type and Model Name		
c	Aux Voltage (Volts)		



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

d	Number of normally contacts	NO / NC /Change Over	NO / NC/Change Over
e	Operating coil VA burden		
f	Whether High Impedance Type		
g	Whether self reset type or hand reset type		
h	Type of Flag indicator		
i	Operating Time		
j	Reset Time		
k	Draw out or non-drawout type		
l	Case finish		
32	ON/OFF switch for Spring charging motor  Make , Model & Rating		
33	TTB for TOD meter  Make & Model No.		
34	Whether Removable HV Cable gland plate is provided with hole suitable for 3 core 300sq.mm XLPE cable?		
35	Capacitive Voltage indicator for monitoring whether the Cable is Live or Dead Make/ Model No.		
36	33kV Cable Termination Height from gland plate level.		
37	Maximum Closing Time of Circuit Breaker (ms)		
38	Maximum Opening Time of Circuit Breaker (ms)		



## SUPPLY CHAIN MANAGEMENT

Thiruvananthapuram

### TECHNICAL SPECIFICATION

#### 33 kV INDOOR VCB 3 PANEL SETS AND 5 PANEL SETS

Doc. #: **SCM-SPEC/XM/3&5 Panel**

Rev.#: 0

Effective Date-**21/04/2021**

**Name and Address the Bidder**